



*Selection guide ..... page 3/2*

### Complete switches, 10 A

- Front mounting by Ø 16 or Ø 22 mm hole,  
with 30 x 30 mm front plate ..... *page 3/8*

### Complete switches, 12 and 20 A

- Front mounting, "multi-fixing" or by Ø 22 mm hole,  
with 45 x 45 mm front plate
  - Switches ..... *page 3/20*
  - Stepping switches ..... *page 3/23*
  - Reversing and changeover switches ..... *page 3/29*
  - Ammeter switches ..... *page 3/32*
  - Voltmeter switches ..... *page 3/32*

### Adaptable sub-assemblies, 12 and 20 A

- Bodies (contact blocks + fixing plate)
  - Switches ..... *page 3/34*
  - Changeover switches ..... *page 3/39*
  - Encoded output switches ..... *page 3/41*
  - Paralelling switches ..... *page 3/44*
  - Stepping switches ..... *pages 3/46 and 3/59*
  - Ammeter switches ..... *page 3/56*
  - Voltmeter switches ..... *page 3/57*
  - Multi-circuit switches ..... *page 3/60*
  - Reversing switches ..... *page 3/61*
  - Star-delta switches and reversing star-delta switches ..... *page 3/62*
  - Pole change switches and reversing pole change switches ..... *page 3/63*
- Operating heads
  - For "multi-fixing" or Ø 22 mm hole, front mounting bodies ..... *page 3/66*
  - For 4 hole, rear mounting bodies ..... *page 3/67*
- Legends
  - For multi-fixing heads ..... *page 3/68*
  - For Ø 22 mm hole mounting heads with plastic bezel ..... *page 3/69*
  - For Ø 22 mm hole mounting heads with chromium plated  
metal bezel ..... *page 3/70*
  - Legend holders for heads ..... *page 3/71*

### Switches, 10 and 16 A, mounted in plastic enclosure

- Emergency stop switches ..... *page 3/78*
- OFF-ON switches ..... *page 3/79*

### Complete switches, 12 A with key operated lock

- Front mounting by 6 screws Ø 5.2 mm, with 55 x 100 mm front plate
  - Stepping switches, 2 to 5 step ..... *page 3/80*
  - Start selector switches ..... *page 3/84*
  - Changeover switches ..... *page 3/85*

### Complete switches, 32 to 150 A

- With 64 x 64 mm front plate (32 to 63 A ratings) and 88 x 88 mm  
front plate (115 and 150 A ratings) ..... *page 3/88*

<b>Applications</b>	Used in building control panels and consoles, type K cam switches allow control of processes and utilities in industry and buildings and direct control for simple machines.	
<b>Functions</b>		
Off-On/On-Off switches	1 to 4-pole	1 to 6-pole
Stepping switches	2 to 4-position, 1 and 2-pole	2 to 12-position, 1 to 4-pole
Changeover switches	1 to 4-pole	1 to 5-pole
Measurement switches	Voltmeter and ammeter	Voltmeter and ammeter
Reversing switches	–	2 and 3-pole
Reversing star-delta switches	–	–
Pole change switches	–	2 and 3-speed



<b>Conventional rated thermal current (I<sub>th</sub>)</b>	<b>10 A</b>	<b>12 A</b>
<b>Rated insulation voltage (U<sub>i</sub>)</b>	440 V	690 V
<b>Electrical operating characteristics</b>	AC-15 - A300 240 V - 3 A	AC-3 - 3-phase 230 V - 1.1 kW - 4.6 A AC-15 230 V - 3 A
<b>Front plate degree of protection</b>	IP 65	IP 40 IP 65 (with seal)
<b>Product composition</b>	Complete switches	Complete switches Adaptable sub-assemblies Special products (please consult your Regional Sales Office)
<b>Compatibility</b>	Ø 16 and Ø 22 control and signalling units	Ø 22 control and signalling units
<b>Fixing</b>		
Front mounting	Single Ø 16 or Ø 22 hole	Multi-fixing Single Ø 22 hole
Rear mounting	–	Screw fixing, 4 holes on 36 mm centres
<b>Front plate dimensions (mm)</b>	30 x 30	45 x 45 60 x 60 (adaptable sub-assemblies)
<b>Operating heads</b>	Black standard handle Metallic legend, black marking	Black and red standard and long handles Key operator Metallic head Metallic legend with black marking or black legend with white marking
<b>Approvals</b>	cULus IEC/EN 60947-3 IEC/EN 60947-5-1	UL-CSA IEC/EN 60947-3 IEC/EN 60947-5-1
<b>Type</b>	<b>Type K10</b>	<b>Type K1/K2</b>
<b>Cam switch model</b>	<b>K10 ●</b>	<b>K1 ●</b>
<b>Pages</b>	3/8 to 3/12	3/20 to 3/73 and 3/80 to 3/85

1 to 6-pole	1 to 6-pole
2 to 12-position, 1 to 4-pole	–
1 to 5-pole	1 to 4-pole
–	–
2 and 3-pole	2 and 3-pole
Star-delta	Star-delta
2 and 3-speed	2-speed



<b>20 A</b> 690 V	<b>32 A</b> 690 V	<b>50 A</b> 690 V	<b>63 A</b> 690 V	<b>115 A</b> 690 V	<b>150 A</b> 690 V
AC-3 - 3-phase 230 V - 2.2 kW - 8.3 A	AC-3 - 3-phase 230 V - 5.5 kW	AC-3 - 3-phase 230 V - 7.5 kW	AC-3 - 3-phase 230 V - 11 kW	AC-3 - 3-phase 230 V - 15 kW	AC-3 - 3-phase 230 V - 22 kW
AC-15 230 V - 4 A	AC-15 230 V - 14 A	AC-15 230 V - 16 A	–	–	–

IP 40

Complete switches

–

By 4 holes on 48 mm centres

By 4 holes on 68 mm centres

Screw fixing, 4 holes on 48 mm centres

Screw fixing, 4 holes on 68 mm centres

64 x 64

88 x 88

Black standard handle  
Metallic legend, black marking

cULus  
IEC/EN 60947-3

Type K30...K150

<b>K2 ●</b>	<b>K30 ●</b>	<b>K50 ●</b>	<b>K63 ●</b>	<b>K115 ●</b>	<b>K150 ●</b>
3/20 to 3/73	3/88 to 3/92				

# Cam switches

## Series K

### Functions panorama

3

Functions		Complete switches 10 A
		See pages
Switches	with 60° switching angle	3/8
	with 45° switching angle	–
	with 90° switching angle	–
	ON-OFF with spring return from 30° to "0" position	–
	OFF-ON with spring return from 30° to "0" position	–
	OFF-ON with spring return from 120° to 90°	–
	OFF-ON with spring return from 30° and from 330° to "0" position	–
	with 90° switching angle	–
	OFF-ON with 45° switching angle	–
	OFF-ON with momentary-contact function	–
	paralleling with "0" position	–
OFF-ON changeover switches	with spring return from 240° to 270° and from 120° to 90°	–
Stepping switches	single-pole with or without "0" position	3/8, 3/9
	2-pole with or without "0" position	3/9, 3/10
	2 to 5 step, single-pole, with or without "0" position	–
	2 to 5 step, 2-pole, with or without "0" position	–
	2 and 3 step, 3-pole, with or without "0" position	–
	2 to 11 step, single-pole, with or without "0" position	–
	2 to 6 step, 2-pole, with or without "0" position	–
	2 to 6 step, 3-pole, with or without "0" position	–
	2 to 5 step, 4-pole, with or without "0" position	–
	2 and 3 step, with "0" position + left-hand position	–
	3 step, without "0" position	–
	4 step, 4-pole, without "0" position	–
	2 step, with "0" position	–
	3 step, 2-pole, with "0" position	–
	5 step, 2-pole, with "0" position	–
Changeover switches	spring return to "0" position	3/10
	with or without "0" position	3/10
	with spring return from 315° and from 45° to "0" position	–
	1 to 4-pole with "0" position	–
	1 to 4-pole without "0" position	–
	with momentary-contact function	–
	with spring return from 240° to 270° and from 120° to 90°	–
	star-delta	–
	pole change	–
Voltmeter switches	with "0" position	3/11
	without "0" position	–
Ammeter switches	with "0" position	3/11
	without "0" position	–
Selector switches	BCD encoded output, with "0" position	–
	BCD encoded output, without "0" position	–
	multi-circuit	–
	star-delta	–
Reversing switches	with "0" position	–
	with spring return from 330° and from 30° to "0" position	–
Changeover switches	1-pole, 2-pole, 3-pole with "0" position	–
		–
Pole change switches	for 2-speed motors	–
	for 3-speed motors	–
Start selector switches	3-position with "0" position	–
	4-position with "0" position	–
Starting switches	star-delta	–
	pole change	–

	Complete switches 12 and 20 A	Complete switches 12 A, with key operated lock	Adaptable sub- assemblies 12 and 20 A	Complete switches 32 to 150 A
	See pages	See pages	See pages	See pages
	–	–	–	3/88
	3/20	–	3/34	–
	3/20	–	–	3/89
	3/21	–	3/36	–
	3/21	–	3/36	–
	3/22	–	3/36	–
	3/22	–	3/37	–
	–	–	3/35	–
	–	–	3/36	–
	–	–	3/37	–
	–	–	3/44, 3/45	–
	–	–	3/37	–
	–	–	–	–
	–	–	–	–
	3/23, 3/24	–	–	–
	3/25, 3/26	–	–	–
	3/27, 3/28	–	–	–
	–	–	3/46, 3/47, 3/48, 3/49	–
	–	–	3/50, 3/51	–
	–	–	3/52, 3/53	–
	–	–	3/54, 3/55	–
	–	–	3/59	–
	–	3/80	–	–
	–	3/81	–	–
	–	3/82	–	–
	–	3/83	–	–
	–	3/83	–	–
	–	–	–	–
	–	–	3/38, 3/39, 3/40	3/90
	3/29	–	3/40	–
	3/29	–	–	–
	3/29	–	–	–
	–	–	3/40	–
	–	–	3/40	–
	–	–	3/62, 3/63	3/91
	–	–	3/64	–
	3/32, 3/33	–	3/57, 3/58	–
	3/32, 3/33	–	3/57, 3/58	–
	3/30, 3/31	–	3/56	–
	3/30, 3/31	–	3/56	–
	–	–	3/41, 3/42	–
	–	–	3/42, 3/43	–
	–	–	3/60	–
	–	–	3/62	–
	–	–	3/61	3/92
	–	–	3/61	–
	–	3/85	–	–
	–	–	3/63, 3/64	–
	–	–	3/65	–
	–	3/84	–	–
	–	3/85	–	–
	–	–	–	3/91
	–	–	–	3/92

# Cam switches

## Complete switches, 10 A


The range of K10 cam switches (10 A rating) comprises only complete switches. These products are more specifically designed for process control applications:

- compact size,
- easy to integrate with other Ø 16 and Ø 22 mm units,
- selection functions.

### Complete switches

- switches
- stepping switches
- reversing switch
- changeover switches
- voltmeter switches
- ammeter switches


### Front mounting



By Ø 16.3 or Ø 22.3 mm hole


### Mounting

### Ø 16 or Ø 22 hole fixing




Locking/unlocking of the body-head assembly by spigot

### Ø 16 hole fixing



### Ø 22 hole fixing



# Cam switches

Complete switches, 10 A

Front mounting by Ø 16 or Ø 22 mm hole

With 30 x 30 mm front plate

## Environment

Conformity to standards	IEC/EN 60947-3 IEC/EN 60947-5-1
Product certifications	cULus
Protective treatment	Standard version: "TC"
Ambient air temperature	For operation: - 20...+ 55 °C For storage: - 40...+ 70 °C
Electric shock protection	Class II, conforming to IEC 60536
Degree of protection	IP 65 conforming to IEC 60529 (operating head) IP 20 (contact block)
Mechanical life	1 million operating cycles

## Contact block characteristics

Rated operational characteristics	AC-15, A300	–	240 V	3 A
			120 V	6 A
	AC-21A, AC-1	–	400 V	10 A
	UL/Canada Heavy Duty A300	3-phase	110/120 V	0.75 hp
			220/240 V	1 hp
		single-phase	110/120 V	0.33 hp
			220/240 V	0.75 hp
	AC-23A	3-phase	220/240 V	1.8 kW
		single-phase	110/120 V	0.37 kW
			220/240 V	0.75 kW
d.c. current Ie resistive load	1 contact	24 V	10 A	
		110 V	0.7 A	
		220 V	0.3 A	
Short-circuit protection	10 A cartridge fuse type gG			
Conventional thermal current (Ith)	10 A			
Rated insulation voltage (Ui)	440 V, degree of pollution 3, conforming to IEC 60947-1			
Contact operation	Slow break			
Terminal referencing	Conforming to CENELEC EN 50013			
Rated impulse withstand voltage (U imp)	4 kV conforming to IEC 60947-1			
Electrical reliability	Failure rate < 1 fault for 100 million operating cycles (--- 24 V PLC inputs)			
Connection	Captive screw clamp terminals Clamping capacity: 2 x 1.5 mm²			

Cam switches

Complete switches, 10 A  
Front mounting by Ø 16 or Ø 22 mm hole  
With 30 x 30 mm front plate



K10 B002ACH

3

Switches

Wiring diagram and switching programme	Marking and switch position	Number of poles	Reference	Weight kg
		1	K10 A001ACH	0.030
		2	K10 B002ACH	0.035
		3	K10 C003ACH	0.045
		4	K10 D004ACH	0.045

Stepping switches, single-pole, with "0" position

Wiring diagram and switching programme	Marking and switch position	Number of steps	Reference	Weight kg
		2 + "0" position	K10 B002QCH	0.035
		3 + "0" position	K10 C003QCH	0.045
		4 + "0" position	K10 D004QCH	0.045











K10 D004QCH

Cam switches

Complete switches, 10 A  
Front mounting by Ø 16 or Ø 22 mm hole  
With 30 x 30 mm front plate



K10 D012QCH

Stepping switches, 2-pole, with "0" position				
Wiring diagram and switching programme	Marking and switch position	Number of steps	Reference	Weight kg
		2 + "0" position	K10 D012QCH	0.045
		3 + "0" position	K10 F013QCH	0.055
Stepping switches, single-pole, without "0" position				
		3	K10 C003NCH	0.045
		4	K10 D004NCH	0.045

Cam switches

Complete switches, 10 A  
Front mounting by Ø 16 or Ø 22 mm hole  
With 30 x 30 mm front plate

3



K10 B006TCH



K10 F003UCH

Stepping switches, 2-pole, without “0” position

Wiring diagram and switching programme	Marking and switch position	Number of steps	Reference	Weight kg
		3	K10 F013NCH	0.055

Changeover switch with spring return to “0” position

Wiring diagram and switching programme	Marking and switch position	Number of poles	Reference	Weight kg
		1	K10 B006TCH	0.035

Changeover switches with “0” position

Wiring diagram and switching programme	Marking and switch position	Number of poles	Reference	Weight kg
		1	K10 B001UCH	0.035
2-pole		2	K10 D002UCH	0.045
3-pole		3	K10 F003UCH	0.055
4-pole		4	K10 H004UCH	0.065

Changeover switches without “0” position

Wiring diagram and switching programme	Marking and switch position	Number of poles	Reference	Weight kg
		1	K10 B011UCH	0.035
2-pole		2	K10 D012UCH	0.045
3-pole		3	K10 F013UCH	0.055
4-pole		4	K10 H014UCH	0.065

Cam switches

Complete switches, 10 A  
Front mounting by Ø 16 or Ø 22 mm hole  
With 30 x 30 mm front plate



K10 F027MCH

Voltmeter switches

For measurements between 3 phases and between 1 phase and neutral

Wiring diagram and switching programme	Marking and switch position	Reference	Weight kg
		K10 F027MCH	0.055

For measurements between 3 phases, with "0" position

		K10 D024MCH	0.045



K10 F003MCH




Ammeter switches

For 3 circuits, with "0" position

		K10 F003MCH	0.055

# Cam switches

Complete switches, 10 A  
Front mounting by Ø 16 or Ø 22 mm hole  
With 30 x 30 mm front plate  
Accessories




Legend holders				
Description		Sold in lots of	Unit reference	Weight kg
For Ø 22 mm hole fixing	With metallic finish legend	25	Z227N	0.060

Accessories				
Description	Colour	Sold in lots of	Unit reference	Weight kg
Blanking plug	Black	10	Z33	0.060
Nut wrench	—	5	Z201	0.020

# Cam switches

Complete switches, 10 A  
Front mounting by Ø 16 or Ø 22 mm hole  
With 30 x 30 mm front plate


Cam switches, 10 A



	a
K10 A, B	51
K10 C, D	63
K10 F	75
K10 H	87


e: support panel thickness 0.5 to 5 mm.

Ø 16 and Ø 22 mm panel cut-outs





Convention used for switching programme representation

Link positions (factory mounted)



Graphic representation of switching positions and spring return to "0" position



Angular position of switch



# Cam switches


Complete switches and adaptable sub-assemblies, 12 and 20 A

The cam switch range comprises the equally dimensioned and similar looking products of the K1 (12 A rating) series and K2 (20 A rating) series. Both series feature complete switches and adaptable sub-assemblies for user assembly.

## Complete switches

### Front mounting


- switches
- stepping switches (2 to 5 step)
- reversing and 1 to 4-pole changeover switches
- ammeter and voltmeter switches



"Multi-fixing"

K1● ●●●●H, K2● ●●●●H


See pages 3/20 to 3/27



By Ø 22 mm hole

K1● ●●●●H, K2● ●●●●H

See pages 3/20 to 3/27



Front mounting by 6 screws  
Ø 5.2 mm and 55 x 100 mm  
front plate


K1● ●●●●Z●

See pages 3/80 to 3/85

## Switches for user assembly

### Front mounting

#### Body sub-assembly



"Multi-fixing"

K1● ●●●●L, K2● ●●●●LL

See pages 3/34 to 3/65

With blank legend

K●G 3H

See page 3/66

With marked legend

KCG 3H

See page 3/66


Without legend

KDG 3H

See page 3/66

#### Head sub-assembly


- With 45 x 45 mm front plate and 35 mm handle



With marked legend

KCG 3Y

See page 3/66



Without legend

KDG 3Y

See page 3/66


# Cam switches

Complete switches and adaptable sub-assemblies, 12 and 20 A

Switches for user assembly (continued)

Front mounting (continued)


Body sub-assembly




With Ø 22 mm hole  
**K1●●●●●, K2●●●●●L**  
See pages 3/34 to 3/65

Head sub-assembly


■ With 45 x 45 mm front plate and 35 mm handle



With blank legend  
**K●C 1H**  
See page 3/66



With marked legend (1)  
**K●C 1●●**  
See page 3/66




Without legend  
**KDC 1●●**  
See page 3/66




Head sub-assembly

■ With 45 x 45 mm front plate and key operator




With blank legend  
**K●C 1●**  
See page 3/66




Without legend  
**KDC 1●**  
See page 3/66

Head sub-assembly


■ With 60 x 60 mm front plate and 42 mm handle



With blank legend  
**K●D 1H**  
See page 3/66



With marked legend  
**KCD 1●●**  
See page 3/66




Without legend  
**KDD 1H**  
See page 3/66




Head sub-assembly

■ With 60 x 60 mm front plate and key operator



With blank legend  
**K●D 1●**  
See page 3/67



Without legend  
**KDD 1●**  
See page 3/67

Head sub-assembly

■ Circular with plastic bezel



Key operator  
**K●A 1●**  
See page 3/67



35 mm handle  
**K●A 1H**  
See page 3/67

(1) With or without padlocking device.


# Cam switches

Complete switches and adaptable sub-assemblies, 12 and 20 A

## Switches for user assembly (continued)

### Front mounting (continued)

#### Body sub-assembly



#### Head sub-assembly

##### ■ Circular with metal bezel



With Ø 22 mm hole and metal mounting plate

**K1●●●●K, K2●●●●X**

See pages 3/34 to 3/65

Standard handle

**KAX Z1M1●**

See page 3/67

Long handle

**KAX Z1C1●**

See page 3/67


Key operator

**KAX Z1S1●●**

See page 3/67

### Rear mounting

#### Body sub-assembly




With 4 holes

**K1●●●●, K2●●●●**

See pages 3/34 to 3/65

#### Head sub-assembly

##### ■ With 45 x 45 mm front plate and 35 mm handle



With blank legend

**K●E 1H**

See page 3/67

With marked legend (1)

**KCE 1●**

See page 3/67


Without legend

**KDE 1●**

See page 3/67

#### Head sub-assembly

##### ■ With 60 x 60 mm front plate and 42 mm handle



With blank legend

**K●F 1H**

See page 3/67

With marked legend

**KCF 1MH**

See page 3/67

Without legend

**KDF 1H**

See page 3/67

(1) With or without padlocking device.

## Accessories

Various accessories complement the K1 - K2 cam switch range: legends, legend holders, terminal covers, seals, etc. See pages 3/68 to 3/73.

## Switches with specific schemes

If you cannot find a standard switching programme listed in this catalogue to suit your application, please consult your Regional Sales Office.

## Cam switches




Complete switches and adaptable sub-assemblies, 12 and 20 A

The cam switches are available to suit various mounting and fixing methods.

### Fixing

#### Front mounting



By means of "multi-fixing" front plate, using 2 or 4 screws



The "multi-fixing" concept enables the switch to be panel mounted using the most commonly used fixing centre dimensions. See drawing to left.

Fixing by 6 screws Ø 5.2 mm and 55 x 100 mm front plate.

By means of single Ø 22 mm hole




Ø 22.5 mm cut-out.  
Head attaches to plate using 1/4 turn bayonet locking and secured on panel by 2 needle screws.

Ø 22.5 mm cut-out with anti-rotation notch.  
Head clips into body and secured on panel by fixing nut.

#### Rear mounting

By means of 4 holes



Switch can be directly mounted on backplate using 4 screws.  
For DIN rail mounting, an adaptor is available as an accessory. See page 3/75.

# Cam switches

Complete switches and adaptable sub-assemblies, 12 to 20 A

## Characteristics

### Environment

Cam switch type			K 1		K 2	
Conformity to standards	For control circuits		IEC/EN 60947-5-1			
	For power circuits		IEC/EN 60947-3			
Product certifications	UL, CSA A300		240 V 0.33 hp single-phase 2-pole	240 V 1 hp 3-phase	240 V 1 hp single-phase	240 V 3 hp 3-phase 2-pole
Protective treatment	Standard version		"TC"			
Ambient air temperature around the device	For operation	°C	- 25...+ 55			
	For storage	°C	- 40...+ 70			
Shock resistance	Conforming to IEC 68-2-27		30 gn			
Vibration resistance	Conforming to IEC 68-2-6		5 gn, 10...150 Hz			
Electric shock protection	Conforming to IEC 536 and NF C 20-030		Class II			
Degree of protection	Conforming to IEC 529 and NF C 20-010		IP 40, for fixing by front plate and 4 screws IP 65, with additional seal			
			IP 65, for Ø 22 mm hole fixing			
Mechanical life	Operating cycles		1 million			







3

Characteristics (continued)						
Contact blocks						
Cam switch type			K 1		K 2	
Rated insulation voltage (Ui)	Conforming to IEC 60947-1 degree of pollution 3		V	690	690	
Conventional thermal current	Screw clamp terminal connections	In open air (Ith)	A	12	20	
		In enclosure (Ithe)	A	10	16	
		Push-on connectors (Ith) (8 A max. per connector)	A	12	16	
Rated operational characteristics	∼ AC-15			Conforming to IEC 947-5-1		
				230 V/3 A		
				230 V/4 A		
	∼ AC-3	3-phase			Conforming to IEC 947-3	
					230 V/1.1 kW/4.6 A	
					230 V/2.2 kW/8.3 A	
					400 V/1.5 kW/3.3 A	
					400 V/4 kW/8 A	
		3-phase			500 V/1.5 kW/2.8 A	
					500 V/4 kW/6.5 A	
					690 V/1.5 kW/1.8 A	
					690 V/4 kW/4.7 A	
		single-phase 2-pole			230 V/0.6 kW	
					230 V/1.3 kW	
					400 V/1.5 kW	
					400 V/2.2 kW	
∼ AC-23 A	3-phase			230 V/1.5 kW/5.6 A		
				230 V/4 kW/14.6 A		
				400 V/2.2 kW/4.8 A		
				400 V/5.5 kW/10.8 A		
∼ AC-21	3-phase			500 V/2.2 kW/3.8 A		
				500 V/5.5 kW/8.9 A		
				690 V/2.2 kW/2.8 A		
				690 V/5.5 kW/6.4 A		
Electrical durability (millions of operating cycles)	AC-3 and AC 23				0.5	
	AC-15 and AC -21				1	
					0.6	
Operating rate (operating cycles/h)	AC-3, AC-23 and AC-21				150	
	AC-15				500	
Rated conditional short-circuit current			kA	10	10	
Short-circuit protection	Cartridge fuse			16 A gG	20 A gG	
Rated impulse withstand voltage	Conforming to IEC 947-1 (Uimp)		kV	6		
	In "isolating" function (Uimp)		kV	4		
Contact operation				Slow break with positive opening operation		
Terminal referencing				Conforming to CENELEC EN 50013		
Connection	Captive screw clamp terminals		mm²	Solid cable, 1 x 2.5		
				Flexible cable, 1 x 2.5 or 2 x 1.5: with or without cable end		
	2 Faston connectors		mm	2.8 x 0.8, please consult your Regional Sales Office.		







# Cam switches

Complete switches, 12 and 20 A  
Front mounting, “multi-fixing” or by Ø 22 mm hole  
With 45 x 45 mm front plate, 35 mm handle and metallic  
legend with black marking

## Switches with 45° switching angle

Wiring diagram and switching programme	Marking and switch position	Front mounting method	Number of poles	Thermal current (Ith)	Reference	Weight
				A		kg
 Kee 0000LH	 Input 1 Input 2 Output 1 Output 2		1	12	K1A 001ALH	0.103
				20	K2A 001ALH	0.103
			2	12	K1B 002ALH	0.113
				20	K2B 002ALH	0.113
			3	12	K1C 003ALH	0.133
				20	K2C 003ALH	0.133
			4	12	K1D 004ALH	0.138
				20	K2D 004ALH	0.138
			5	12	K1E 005ALH	0.158
				20	K2E 005ALH	0.158
			6	12	K1F 006ALH	0.168
				20	K2F 006ALH	0.168
 Kee 0000CH			1	12	K1A 001ACH	0.123
				20	K2A 001ACH	0.123
			2	12	K1B 002ACH	0.133
				20	K2B 002ACH	0.133
			3	12	K1C 003ACH	0.153
				20	K2C 003ACH	0.153
			4	12	K1D 004ACH	0.158
				20	K2D 004ACH	0.158
			5	12	K1E 005ACH	0.178
				20	K2E 005ACH	0.178
			6	12	K1F 006ACH	0.188
				20	K2F 006ACH	0.188

## Switches with 90° switching angle


			2	12	K1B 1002HLH	0.130
				20	K2B 1002HLH	0.130
			3	12	K1C 003HLH	0.135
				20	K2C 003HLH	0.135
			4	12	K1D 004HLH	0.140
				20	K2D 004HLH	0.140
			2	12	K1B 1002HCH	0.150
				20	K2B 1002HCH	0.150
			3	12	K1C 003HCH	0.155
				20	K2C 003HCH	0.155
			4	12	K1D 004HCH	0.160
				20	K2D 004HCH	0.160

Cam switches

Complete switches, 12 and 20 A  
Front mounting, “multi-fixing” or by Ø 22 mm hole  
With 45 x 45 mm front plate, 35 mm handle and metallic  
legend with black marking



ON-OFF switches with spring return from 30° to “0” position						
Wiring diagram and switching programme	Marking and switch position	Front mounting method	Number of poles	Thermal current (Ith)	Reference	Weight
				A		kg
		“Multi-fixing”	1	12	K1A 002TLH	0.105
				20	K2A 002TLH	0.105
		By Ø 22 mm hole	1	12	K1A 002TCH	0.125
				20	K2A 002TCH	0.125





OFF-ON switches with spring return from 30° to “0” position						
Wiring diagram and switching programme	Marking and switch position	Front mounting method	Number of poles	Thermal current (Ith)	Reference	Weight
				A		kg
		“Multi-fixing”	1	12	K1A 001TLH	0.105
				20	K2A 001TLH	0.105
		By Ø 22 mm hole	1	12	K1A 001TCH	0.125
				20	K2A 001TCH	0.125





Cam switches




Complete switches, 12 and 20 A  
Front mounting, “multi-fixing” or by Ø 22 mm hole  
With 45 x 45 mm front plate, 35 mm handle and metallic  
legend with black marking



OFF-ON switches with spring return from 120° to 90°

Wiring diagram and switching programme	Marking and switch position	Front mounting method	Number of poles	Thermal current (Ith)	Reference	Weight	
		“Multi-fixing”	1	12	K1B 003TLH	0.115	
				20	K2B 003TLH	0.115	
			By Ø 22 mm hole	1	12	K1B 003TCH	0.135
					20	K2B 003TCH	0.135











OFF-ON switches with spring return from 30° and from 330° to “0” position

 K●●●●●CH			"Multi-fixing"	1	12	K1B 004TLH	0.115
					20	K2B 004TLH	0.115
				By Ø 22 mm hole	12	K1B 004TCH	0.135
					20	K2B 004TCH	0.135



Cam switches









Complete switches, 12 and 20 A  
Front mounting, “multi-fixing” or by Ø 22 mm hole  
With 45 x 45 mm front plate, 35 mm handle and metallic  
legend with black marking

Stepping switches (2 to 5 step), single-pole, with “0” position					
Wiring diagram and switching programme	Marking and switch position	Front mounting method	Thermal current (Ith)	Reference	Weight
			A		kg
 KeeeeeLH			2 step + “0”		
			12	K1B 002QLH	0.115
			20	K2B 002QLH	0.115
			12	K1B 002QCH	0.135
			20	K2B 002QCH	0.135
 KeeeeeCH			3 step + “0”		
			12	K1C 003QLH	0.135
			20	K2C 003QLH	0.135
			12	K1C 003QCH	0.155
			20	K2C 003QCH	0.155
			4 step + “0”		
			12	K1D 004QLH	0.140
			20	K2D 004QLH	0.140
			12	K1D 004QCH	0.160
			20	K2D 004QCH	0.160
			5 step + “0”		
			12	K1E 005QLH	0.160
			20	K2E 005QLH	0.160
			12	K1E 005QCH	0.180
			20	K2E 005QCH	0.180

Cam switches









Complete switches, 12 and 20 A  
Front mounting, “multi-fixing” or by Ø 22 mm hole  
With 45 x 45 mm front plate, 35 mm handle and metallic  
legend with black marking

Stepping switches (2 to 5 step), single-pole, without “0” position

Wiring diagram and switching programme	Marking and switch position	Front mounting method	Thermal current (Ith)	Reference	Weight
			A		kg
 K00000LH	 	 By Ø 22 mm hole	2 step		
			12	K1B 002NLH	0.115
			20	K2B 002NLH	0.115
			12	K1B 002NCH	0.135
			20	K2B 002NCH	0.135
			3 step		
			12	K1C 003NLH	0.135
			20	K2C 003NLH	0.135
			12	K1C 003NCH	0.155
			20	K2C 003NCH	0.155
 K00000CH	 	 By Ø 22 mm hole	4 step		
			12	K1D 004NLH	0.140
			20	K2D 004NLH	0.140
			12	K1D 004NCH	0.160
			20	K2D 004NCH	0.160
			5 step		
			12	K1E 005NLH	0.160
			20	K2E 005NLH	0.160
			12	K1E 005NCH	0.180
			20	K2E 005NCH	0.180

Cam switches













Complete switches, 12 and 20 A  
Front mounting, “multi-fixing” or by Ø 22 mm hole  
With 45 x 45 mm front plate, 35 mm handle and metallic  
legend with black marking

Stepping switches (2 to 5 step), 2-pole, with “0” position					
Wiring diagram and switching programme	Marking and switch position	Front mounting method	Thermal current (Ith)	Reference	Weight
			A		kg
 Kee 0000LH			2 step + “0”		
			12	K1D 012QLH	0.140
			20	K2D 012QLH	0.140
			12	K1D 012QCH	0.160
			20	K2D 012QCH	0.160
 Kee 0000CH			3 step + “0”		
			12	K1F 013QLH	0.170
			20	K2F 013QLH	0.170
			12	K1F 013QCH	0.190
			20	K2F 013QCH	0.190
			4 step + “0”		
			12	K1H 014QLH	0.195
			20	K2H 014QLH	0.195
			12	K1H 014QCH	0.215
			20	K2H 014QCH	0.215
			5 step + “0”		
			12	K1K 015QLH	0.225
			20	K2K 015QLH	0.225
			12	K1K 015QCH	0.245
			20	K2K 015QCH	0.245

Cam switches

Complete switches, 12 and 20 A  
Front mounting, “multi-fixing” or by Ø 22 mm hole  
With 45 x 45 mm front plate, 35 mm handle and metallic  
legend with black marking

Stepping switches (2 to 5 step), 2-pole, without “0” position

Wiring diagram and switching programme	Marking and switch position	Front mounting method	Thermal current (Ith) A	Reference	Weight kg
 K00 0000LH   K00 0000CH 	 	“Multi-fixing” By Ø 22 mm hole	2 step		
			12	K1D 012NLH	0.140
			20	K2D 012NLH	0.140
			12	K1D 012NCH	0.160
			20	K2D 012NCH	0.160
	 	“Multi-fixing” By Ø 22 mm hole	3 step		
			12	K1F 013NLH	0.170
			20	K2F 013NLH	0.170
			12	K1F 013NCH	0.190
			20	K2F 013NCH	0.190
	 	“Multi-fixing” By Ø 22 mm hole	4 step		
			12	K1H 014NLH	0.195
			20	K2H 014NLH	0.195
			12	K1H 014NCH	0.215
			20	K2H 014NCH	0.215
	 	“Multi-fixing” By Ø 22 mm hole	5 step		
			12	K1K 015NLH	0.225
			20	K2K 015NLH	0.225
			12	K1K 015NCH	0.245
			20	K2K 015NCH	0.245


Cam switches

Complete switches, 12 and 20 A  
Front mounting, “multi-fixing” or by Ø 22 mm hole  
With 45 x 45 mm front plate, 35 mm handle and metallic  
legend with black marking

Stepping switches (2 and 3 step), 3-pole, with “0” position



K00000LH





“Multi-fixing”

By Ø 22 mm hole

Thermal current (Ith)	Reference	Weight
A		kg
2 step + “0”		
12	K1F 022QLH	0.170
20	K2F 022QLH	0.170
12	K1F 022QCH	0.190
20	K2F 022QCH	0.190



K00000CH



“Multi-fixing”









By Ø 22 mm hole

Thermal current (Ith)	Reference	Weight
A		kg
3 step + “0”		
12	K1I 023QLH	0.215
20	K2I 023QLH	0.215
12	K1I 023QCH	0.235
20	K2I 023QCH	0.235

Cam switches

Complete switches, 12 and 20 A  
Front mounting, “multi-fixing” or by Ø 22 mm hole  
With 45 x 45 mm front plate, 35 mm handle and metallic  
legend with black marking

Stepping switches (2 and 3 step), 3-pole, without “0” position

Wiring diagram and switching programme	Marking and switch position	Front mounting method	Thermal current (Ith)	Reference	Weight
			A		kg
 <i>K1F 022NLH</i>	 		<b>2 step</b>		
			12	K1F 022NLH	0.170
			20	K2F 022NLH	0.170
			12	K1F 022NCH	0.190
			20	K2F 022NCH	0.190
 <i>K1I 023NLH</i>	 		<b>3 step</b>		
			12	K1I 023NLH	0.215
			20	K2I 023NLH	0.215
			12	K1I 023NCH	0.235
			20	K2I 023NCH	0.235

3



Cam switches

Complete switches, 12 A

Front mounting, “multi-fixing” or by Ø 22 mm hole

With 45 x 45 mm front plate, 35 mm handle and metallic legend with black marking

Ammeter switches



K1F 003MLH



K1F 003MCH

Wiring diagram and switching programme	Marking and switch position	Front mounting method	Thermal current (I <sub>th</sub> )	Reference	Weight
			A		kg
For 3 circuits					
<div><div><div><div>L1</div><div>L2</div><div>L3</div><div>1</div><div>2</div><div>3</div><div>4</div><div>5</div><div>6</div><div>7</div><div>8</div><div>9</div><div>10</div><div>11</div><div>12</div></div><div><div>0</div><div>90</div><div>180</div><div>270</div><div>1</div><div>2</div><div>3</div><div>4</div><div>5</div><div>6</div><div>7</div><div>8</div><div>9</div><div>10</div><div>11</div><div>12</div></div></div><div><div><div>L1</div><div>L2</div><div>L3</div><div>1</div><div>2</div><div>3</div><div>4</div><div>5</div><div>6</div><div>7</div><div>8</div><div>9</div><div>10</div><div>11</div><div>12</div></div><div><div>0</div><div>90</div><div>180</div><div>270</div><div>1</div><div>2</div><div>3</div><div>4</div><div>5</div><div>6</div><div>7</div><div>8</div><div>9</div><div>10</div><div>11</div><div>12</div></div></div></div>	<div><div><div>0</div><div>L3</div><div>L1</div><div>L2</div></div><div><div>0</div><div>270</div><div>90</div><div>180</div></div></div>	<div>“Multi-fixing”</div> <div>By Ø 22 mm hole</div>	<div>With “0” position</div> <div>12</div> <div>12</div>	<div>K1F 003MLH</div> <div>K1F 003MCH</div>	<div>0.170</div> <div>0.190</div>
<div><div><div><div>L1</div><div>L2</div><div>L3</div><div>1</div><div>2</div><div>3</div><div>4</div><div>5</div><div>6</div><div>7</div><div>8</div><div>9</div><div>10</div><div>11</div><div>12</div></div><div><div>0</div><div>90</div><div>180</div><div>270</div><div>1</div><div>2</div><div>3</div><div>4</div><div>5</div><div>6</div><div>7</div><div>8</div><div>9</div><div>10</div><div>11</div><div>12</div></div></div><div><div><div>L1</div><div>L2</div><div>L3</div><div>1</div><div>2</div><div>3</div><div>4</div><div>5</div><div>6</div><div>7</div><div>8</div><div>9</div><div>10</div><div>11</div><div>12</div></div><div><div>0</div><div>90</div><div>180</div><div>270</div><div>1</div><div>2</div><div>3</div><div>4</div><div>5</div><div>6</div><div>7</div><div>8</div><div>9</div><div>10</div><div>11</div><div>12</div></div></div></div>	<div><div><div>L1</div><div>L2</div><div>L3</div></div><div><div>0</div><div>90</div><div>180</div></div></div>	<div>“Multi-fixing”</div> <div>By Ø 22 mm hole</div>	<div>Without “0” position</div> <div>12</div> <div>12</div>	<div>K1F 013MLH</div> <div>K1F 013MCH</div>	<div>0.170</div> <div>0.190</div>

L1

L2

L3

1

2

3

4

5

6

7

8

9

10

11

12

0

90

180

270

1

2

3

4

5

6

7

8

9

10

11

12

L1

L2

L3

1

2

3

4

5

6

7

8

9

10

11

12

0

90

180

270

1

2

3

4

5

6

7

8

9

10

11

12

Cam switches

Complete switches, 12 A

Front mounting, “multi-fixing” or by Ø 22 mm hole

With 45 x 45 mm front plate, 35 mm handle and metallic legend with black marking


Ammeter switches (continued)

Wiring diagram and switching programme	Marking and switch position	Front mounting method	Thermal current (Ith)	Reference	Weight
			A		kg

For 4 circuits





K1H 004MLH




“Multi-fixing”	With “0” position		
	12	K1H 004MLH	0.195
By Ø 22 mm hole	12	K1H 004MCH	0.215



K1H 004MCH



“Multi-fixing”	Without “0” position		
	12	K1H 014MLH	0.195
By Ø 22 mm hole	12	K1H 014MCH	0.215



Cam switches

Complete switches, 12 A  
Front mounting, “multi-fixing” or by Ø 22 mm hole  
With 45 x 45 mm front plate, 35 mm handle and metallic  
legend with black marking



Voltmeter switches

Wiring diagram	Switching programme	Marking and switch position	Front mounting method	Thermal current (Ith)	Reference	Weight
				A		kg

For measurements between 3 phases and neutral



K1D 022MLH




With “0” position			
“Multi-fixing”	12	K1D 023MLH	0.140

By Ø 22 mm hole	12	K1D 023MCH	0.160
-----------------	----	------------	-------





K1D 033MLH



Without “0” position			
“Multi-fixing”	12	K1D 033MLH	0.140


By Ø 22 mm hole	12	K1D 033MCH	0.160
-----------------	----	------------	-------

For measurements between 3 phases of 2 supplies



With “0” position			
“Multi-fixing”	12	K1H 026MLH	0.205

By Ø 22 mm hole	12	K1H 026MCH	0.215
-----------------	----	------------	-------



Without “0” position			
“Multi-fixing”	12	K1H 036MLH	0.205

By Ø 22 mm hole	12	K1H 036MCH	0.215
-----------------	----	------------	-------

# Cam switches

Complete switches, 12 A

Front mounting, “multi-fixing” or by Ø 22 mm hole

With 45 x 45 mm front plate, 35 mm handle and metallic legend with black marking



## Voltmeter switches (continued)

Wiring diagram	Switching programme	Marking and switch position	Front mounting method	Thermal current (Ith)	Reference	Weight
				A		kg

### For measurements between 3 phases and between each of the 3 phases and neutral



K1F 027MLH



“Multi-fixing”

#### With “0” position


12 K1F 027MLH 0.170

By Ø 22 mm hole

12 K1F 027MCH 0.190



K1F 037MLH



“Multi-fixing”



#### Without “0” position

12 K1F 037MLH 0.170

By Ø 22 mm hole

12 K1F 037MCH 0.190

### For measurements between 3 phases




“Multi-fixing”

#### With “0” position

12 K1D 024MLH 0.140

By Ø 22 mm hole

12 K1D 024MCH 0.160



“Multi-fixing”



#### Without “0” position

12 K1D 034MLH 0.140

By Ø 22 mm hole

12 K1D 034MCH 0.160

### For measurements between 3 phases and between 1 phase and neutral




“Multi-fixing”

#### With “0” position

12 K1E 025MLH 0.160

By Ø 22 mm hole

12 K1E 025MCH 0.180



“Multi-fixing”

#### Without “0” position

12 K1E 035MLH 0.160

By Ø 22 mm hole


















12 K1E 035MCH 0.180

# Cam switches

Adaptable sub-assemblies, 12 and 20 A  
Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67

## Switches

Wiring diagram and switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg	
	<b>1-pole</b>				
		Front	Multi-fixing	<b>K●A 001AL</b>	0.091
		By Ø 22 mm hole	<b>K●A 001A</b>		0.075
		Rear		<b>K●A 001AX</b> (2)	0.153
				<b>K●A 501A</b>	0.115
	<b>2-pole</b>				
		Front	Multi-fixing	<b>K●B 002AL</b>	0.101
		By Ø 22 mm hole	<b>K●B 002A</b>		0.085
		Rear		<b>K●B 002AX</b> (2)	0.163
				<b>K●B 502A</b>	0.125
	<b>3-pole</b>				
		Front	Multi-fixing	<b>K●C 003AL</b>	0.121
		By Ø 22 mm hole	<b>K●C 003A</b>		0.105
		Rear		<b>K●C 003AX</b> (2)	0.183
				<b>K●C 503A</b>	0.140
	<b>4-pole</b>				
		Front	Multi-fixing	<b>K●D 004AL</b>	0.126
		By Ø 22 mm hole	<b>K●D 004A</b>		0.110
		Rear		<b>K●D 004AX</b> (2)	0.188
				<b>K●D 504A</b>	0.150
	<b>5-pole</b>				
		Front	Multi-fixing	<b>K●E 005AL</b>	0.146
		By Ø 22 mm hole	<b>K●E 005A</b>		0.130
		Rear		<b>K●E 005AX</b> (2)	0.208
				<b>K●E 505A</b>	0.165
	<b>6-pole</b>				
		Front	Multi-fixing	<b>K●F 006AL</b>	0.156
		By Ø 22 mm hole	<b>K●F 006A</b>		0.140
		Rear		<b>K●F 006AX</b> (2)	0.218
				<b>K●F 506A</b>	0.175
	<b>7-pole</b>				
		Front	Multi-fixing	<b>K●G 007AL</b>	0.176
		By Ø 22 mm hole	<b>K●G 007A</b>		0.160
		Rear		<b>K●G 507A</b>	0.190
	<b>8-pole</b>				
		Front	Multi-fixing	<b>K●H 008AL</b>	0.181
		By Ø 22 mm hole	<b>K●H 008A</b>		0.165
		Rear		<b>K●H 508A</b>	0.195

(1) To order a cam switch with thermal current  $I_{th} = 12\text{ A}$ , replace the ● in the reference by 1.  
Example **K1A 001A**.

To order a cam switch with thermal current  $I_{th} = 20\text{ A}$ , replace the ● in the reference by 2.

Example **K2A 001A**.

(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAX Z1●●●**.


## Cam switches

Adaptable sub-assemblies, 12 and 20 A  
bodies (contact blocks + fixing plate)To combine with operating heads: see pages 3/66  
and 3/67


## Switches (continued)



K00 0000L



## 2-pole



Front

Multi-fixing  
By Ø 22 mm  
holeReference, to  
be completed  
(1)

K0B 1002HL


0.121

K0B 1002H


0.105

K0B 1002HX (2)

0.183



## 3-pole



Front

Multi-fixing  
By Ø 22 mm  
hole

K0C 003HL

0.121

K0C 003H

0.105

K0C 003HX (2)


0.183

Rear

K0C 503H

0.140

## 3-pole with neutral wire terminal and Earth terminal



Front

Multi-fixing  
By Ø 22 mm  
hole

K0C 023HL

0.121

K0C 023H

0.105

K0C 023HX (2)

0.183


Rear

K0C 523H


0.140



K00 0000



## 4-pole



Front

Multi-fixing  
By Ø 22 mm  
hole

K0D 004HL

0.126

K0D 004H

0.110

K0D 004HX (2)


0.188

Rear

K0D 504H

0.150

## 4-pole with neutral wire terminal and Earth terminal



Front

Multi-fixing  
By Ø 22 mm  
hole

K0D 024HL

0.126

K0D 024H

0.110

K0D 024HX (2)

0.188


Rear

K0D 524H


0.150



K0E 5000



## 5-pole



Front

Multi-fixing  
By Ø 22 mm  
hole

K0E 005HL

0.146

K0E 005H

0.130

K0E 005HX (2)


0.208

Rear

K0E 505H

0.165

## 5-pole with neutral wire terminal and Earth terminal



Front

Multi-fixing  
By Ø 22 mm  
hole

K0E 025HL

0.146

K0E 025H

0.130


Rear

K0E 525H


0.165



K0F 0000X



## 6-pole



Front

Multi-fixing  
By Ø 22 mm  
hole

K0F 006HL

0.156

K0F 006H

0.140

K0F 006HX (2)


0.218

Rear

K0F 506H

0.175

## 6-pole with neutral wire terminal and Earth terminal



Front

Multi-fixing  
By Ø 22 mm  
hole

K0F 026HL

0.156

K0F 026H

0.140

Rear

K0F 526H

0.175

(1) To order a cam switch with thermal current  $I_{th} = 12$  A, replace the ● in the reference by 1.

Example K1C 003H.

To order a cam switch with thermal current  $I_{th} = 20$  A, replace the ● in the reference by 2.

Example K2C 003H.

(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAX Z1●●●.

# Cam switches

Adaptable sub-assemblies, 12 and 20 A  
bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66  
and 3/67

3



K00000L

OFF-ON switches					
Wiring diagram	Switching programme	Switch position	Mounting method		Reference, to be completed (1)
			Front	Multi-fixing	K00A 001AL
				By Ø 22 mm hole	K00A 001A
					K00A 001AX (2)
			Rear		K00A 501A
					Weight kg
					0.091
					0.075
					0.153
					0.115



K00000

OFF-ON switches with spring return from 30° to “0” position					
Wiring diagram	Switching programme	Switch position	Mounting method		Reference, to be completed (1)
			Front	Multi-fixing	K00A 001TL
				By Ø 22 mm hole	K00A 001T
					K00A 001TX (2)
			Rear		K00A 501T
					Weight kg
					0.091
					0.075
					0.153
					0.115



K005000

ON-OFF switches with spring return from 30° to “0” position					
Wiring diagram	Switching programme	Switch position	Mounting method		Reference, to be completed (1)
			Front	Multi-fixing	K00A 002TL
				By Ø 22 mm hole	K00A 002T
					K00A 002TX (2)
			Rear		K00A 502T
					Weight kg
					0.091
					0.075
					0.153
					0.115



K00000X

OFF-ON switches with spring return from 120° to 90°					
Wiring diagram	Switching programme	Switch position	Mounting method		Reference, to be completed (1)
			Front	Multi-fixing	K00B 003TL
				By Ø 22 mm hole	K00B 003T
			Rear		K00B 503T
					Weight kg
					0.101
					0.085
					0.125

(1) To order a cam switch with thermal current Ith = 12 A, replace the ● in the reference by 1.  
Example K1A 001A.  
To order a cam switch with thermal current Ith = 20 A, replace the ● in the reference by 2.  
Example K2A 001A.  
(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAX Z1000.



## Cam switches

Adaptable sub-assemblies, 12 and 20 A

Bodies (contact blocks + fixing plate)



To combine with operating heads: see pages 3/66 and 3/67

## OFF-ON switches with spring return from 30° and from 330° to "0" position

Wiring diagram and switching programme	Switch position	Mounting method		Reference, to be completed (1)	Weight kg
		Front	Multi-fixing	<b>K●B 004TL</b>	0.101
			By Ø 22 mm hole	<b>K●B 004T</b>	0.085
		Rear		<b>K●B 504T</b>	0.115






## OFF-ON switches with momentary-contact function

Wiring diagram and switching programme	Switch position	Mounting method		Reference, to be completed (1)	Weight kg
		Front	Multi-fixing	<b>K●B 001DL</b>	0.101
			By Ø 22 mm hole	<b>K●B 001D</b>	0.085
		Rear	<b>K●B 001DX</b> (2)	0.163	
			<b>K●B 501D</b>	0.125	



## OFF-ON changeover switches with spring return from 240° to 270° and from 120° to 90°

Wiring diagram and switching programme	Switch position	Mounting method		Reference, to be completed (1)	Weight kg
		Front	Multi-fixing	<b>K●D 005TL</b>	0.126
			By Ø 22 mm hole	<b>K●D 005T</b>	0.110
		Rear	<b>K●D 505T</b>	0.150	











(1) To order a cam switch with thermal current  $I_{th} = 12$  A, replace the ● in the reference by 1.Example **K1B 004T**.To order a cam switch with thermal current  $I_{th} = 20$  A, replace the ● in the reference by 2.Example **K2B 004T**.(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAX Z1●●●**.

# Cam switches

Adaptable sub-assemblies, 12 and 20 A  
Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67

## Changeover switches with "0" position

Wiring diagram and switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
  <b>K00 0000L</b>	1-pole	Front Multi-fixing By Ø 22 mm hole	<b>K0B 001UL</b>	0.101
			<b>K0B 001U</b>	0.085
			<b>K0B 001UX (2)</b>	0.163
			<b>K0B 501U</b>	0.125
  <b>K00 0000</b>	2-pole	Front Multi-fixing By Ø 22 mm hole	<b>K0D 002UL</b>	0.126
			<b>K0D 002U</b>	0.110
			<b>K0D 002UX (2)</b>	0.188
			<b>K0D 502U</b>	0.150
  <b>K00 5000</b>	3-pole	Front Multi-fixing By Ø 22 mm hole	<b>K0F 003UL</b>	0.156
			<b>K0F 003U</b>	0.140
			<b>K0F 003UX (2)</b>	0.218
			<b>K0F 503U</b>	0.175
  <b>K00 5000</b>	4-pole	Front Multi-fixing By Ø 22 mm hole	<b>K0H 004UL</b>	0.181
			<b>K0H 004U</b>	0.165
			<b>K0H 004UX (2)</b>	0.243
			<b>K0H 504U</b>	0.195
  <b>K00 5000</b>	5-pole	Front Multi-fixing By Ø 22 mm hole	<b>K0K 005UL</b>	0.211
			<b>K0K 005U</b>	0.195
			<b>K0K 005UX (2)</b>	0.273
			<b>K0K 505U</b>	0.210

(1) To order a cam switch with thermal current  $I_{th} = 12$  A, replace the ● in the reference by 1.  
Example **K1B 001U**.  
To order a cam switch with thermal current  $I_{th} = 20$  A, replace the ● in the reference by 2.  
Example **K2B 001U**.  
(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAX Z1000**.


# Cam switches

Adaptable sub-assemblies, 12 and 20 A  
Bodies (contact blocks + fixing plate)


To combine with operating heads: see pages 3/66 and 3/67



K●● 0●●●L



K●● 0●●●



K●● 5●●●



K●● 0●●●X

Changeover switches without "0" position					
Wiring diagram and switching programme	Switch position	Mounting method		Reference, to be completed (1)	Weight kg
	1-pole	Front	Multi-fixing	K●B 011UL	0.101
			By Ø 22 mm hole	K●B 011U	0.085
	Rear			K●B 011UX (2)	0.163
				K●B 511U	0.125
		Front	Multi-fixing	K●D 012UL	0.126
			By Ø 22 mm hole	K●D 012U	0.110
	3-pole			K●D 012UX (2)	0.188
		Rear		K●D 512U	0.150
		Front	Multi-fixing	K●F 013UL	0.156
			By Ø 22 mm hole	K●F 013U	0.140
	Rear			K●F 013UX (2)	0.218
				K●F 513U	0.175
	4-pole	Front	Multi-fixing	K●H 014UL	0.181
			By Ø 22 mm hole	K●H 014U	0.165
	Rear			K●H 014UX (2)	0.243
				K●H 514U	0.195
	5-pole	Front	Multi-fixing	K●K 015UL	0.211
			By Ø 22 mm hole	K●K 015U	0.195
	Rear			K●K 015UX (2)	0.273
				K●K 515U	0.220

(1) To order a cam switch with thermal current Ith = 12 A, replace the ● in the reference by 1.  
Example **K1B 011U**.  
To order a cam switch with thermal current Ith = 20 A, replace the ● in the reference by 2.  
Example **K2B 011U**.  
(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAX Z1●●●**.

## Cam switches

Adaptable sub-assemblies, 12 and 20 A

Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67

## Reversing switches

Wiring diagram	Switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
			Front	Multi-fixing	0.101
			By Ø 22 mm hole	<b>K0B 001UL</b>	0.085
				<b>K0B 001UX</b> (2)	0.163
			Rear	<b>K0B 501U</b>	0.125



K0B 0000L

## Reversing switches with spring return from 315° and from 45° to "0" position

Wiring diagram	Switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
			Front	Multi-fixing	0.101
			By Ø 22 mm hole	<b>K0B 006T</b>	0.085
				<b>K0B 006TX</b> (2)	0.163
			Rear	<b>K0B 506T</b>	0.125



K0B 006TL

## Reversing switches with momentary-contact function

Wiring diagram	Switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
			Front	Multi-fixing	0.121
			By Ø 22 mm hole	<b>K0C 002D</b>	0.105
				<b>K0C 002DX</b> (2)	0.183
			Rear	<b>K0C 502D</b>	0.140



K0C 002DL

## Reversing switches with spring return from 240° to 270° and from 120° to 90° position

Wiring diagram	Switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
			Front	Multi-fixing	0.121
			By Ø 22 mm hole	<b>K0C 007T</b>	0.105
				<b>K0C 507T</b>	0.140



K0C 007TL

(1) To order a cam switch with thermal current  $I_{th} = 12$  A, replace the ● in the reference by 1.

Example **K1B 001U**.

To order a cam switch with thermal current  $I_{th} = 20$  A, replace the ● in the reference by 2.

Example **K2B 001U**.

(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAX Z1000**.

## Cam switches

Adaptable sub-assemblies, 12 A

Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67

## BCD encoded output switches with "0" position

Wiring diagram	Switching programme	Switch position	Mounting method	Reference (1)	Weight kg	
		<b>1 decimal</b>				
			Front	Multi-fixing	<b>K1A 001BL</b>	0.101
			By Ø 22 mm hole	<b>K1A 001B</b>	0.085	
				<b>K1A 001BX</b>	(2) 0.163	
		Rear		<b>K1A 501B</b>	0.125	
		<b>2 decimal</b>				
			Front	Multi-fixing	<b>K1B 002BL</b>	0.101
			By Ø 22 mm hole	<b>K1B 002B</b>	0.085	
				<b>K1B 002BX</b>	(2) 0.163	
		Rear		<b>K1B 502B</b>	0.125	
<b>3 decimal</b>						
	Front	Multi-fixing	<b>K1B 003BL</b>	0.101		
	By Ø 22 mm hole	<b>K1B 003B</b>	0.085			
		<b>K1B 003BX</b>	(2) 0.163			
Rear		<b>K1B 503B</b>	0.125			
<b>4 decimal</b>						
	Front	Multi-fixing	<b>K1C 004BL</b>	0.121		
	By Ø 22 mm hole	<b>K1C 004B</b>	0.105			
		<b>K1C 004BX</b>	(2) 0.183			
Rear		<b>K1C 504B</b>	0.140			
<b>5 decimal</b>						
	Front	Multi-fixing	<b>K1C 005BL</b>	0.121		
	By Ø 22 mm hole	<b>K1C 005B</b>	0.105			
		<b>K1C 005BX</b>	(2) 0.183			
Rear		<b>K1C 505B</b>	0.140			
<b>6 decimal</b>						
	Front	Multi-fixing	<b>K1C 006BL</b>	0.121		
	By Ø 22 mm hole	<b>K1C 006B</b>	0.105			
		<b>K1C 006BX</b>	(2) 0.183			
Rear		<b>K1C 506B</b>	0.140			
<b>7 decimal</b>						
	Front	Multi-fixing	<b>K1C 007BL</b>	0.121		
	By Ø 22 mm hole	<b>K1C 007B</b>	0.105			
		<b>K1C 007BX</b>	(2) 0.183			
Rear		<b>K1C 507B</b>	0.140			
<b>8 decimal</b>						
			Front	Multi-fixing	<b>K1D 008BL</b>	0.126
			By Ø 22 mm hole	<b>K1D 008B</b>	0.110	
				<b>K1D 008BX</b>	(2) 0.188	
		Rear		<b>K1D 508B</b>	0.150	

(1)  $I_{th} = 12$  A.(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAX Z1000**.

Cam switches  
Adaptable sub-assemblies, 12 A  
Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66  
and 3/67

3



BCD encoded output switches with “0” position (continued)				
Wiring diagram and switching programme	Switch position	Mounting method	Reference (1)	Weight kg

 	<b>9 decimal</b>			
	Front	Multi-fixing	K1D 009BL	0.126
		By Ø 22 mm hole	K1D 009B	0.110
	Rear		K1D 009BX (2)	0.188
			K1D 509B	0.150
 	<b>10 decimal</b>			
	Front	Multi-fixing	K1D 010BL	0.126
		By Ø 22 mm hole	K1D 010B	0.110
	Rear		K1D 510B	0.150
 	<b>11 decimal</b>			
	Front	Multi-fixing	K1D 011BL	0.126
		By Ø 22 mm hole	K1D 011B	0.110
	Rear		K1D 511B	0.150







BCD encoded output switches without “0” position				
Wiring diagram and switching programme	Switch position	Mounting method	Reference (1)	Weight kg

 	<b>1 and 2 decimal</b>			
	Front	Multi-fixing	K1B 022BL	0.101
		By Ø 22 mm hole	K1B 022B	0.085
	Rear		K1B 022BX (2)	0.163
			K1B 522B	0.125
 	<b>3 decimal</b>			
	Front	Multi-fixing	K1B 023BL	0.101
		By Ø 22 mm hole	K1B 023B	0.085
	Rear		K1B 023BX (2)	0.163
			K1B 523B	0.125
 	<b>4 decimal</b>			
	Front	Multi-fixing	K1C 024BL	0.121
		By Ø 22 mm hole	K1C 024B	0.105
	Rear		K1C 024BX (2)	0.183
			K1C 524B	0.140
 	<b>5 decimal</b>			
	Front	Multi-fixing	K1C 025BL	0.121
		By Ø 22 mm hole	K1C 025B	0.105
	Rear		K1C 025BX (2)	0.183
			K1C 525B	0.140
 	<b>6 decimal</b>			
	Front	Multi-fixing	K1C 026BL	0.121
		By Ø 22 mm hole	K1C 026B	0.105
	Rear		K1C 026BX (2)	0.183
			K1C 526B	0.140

(1) Ith = 12 A.  
(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAX Z1000.

Cam switches  
Adaptable sub-assemblies, 12 A  
Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66  
and 3/67

BCD encoded output switches without “0” position (continued)					
Wiring diagram and switching programme	Switch position	Mounting method		Reference (1)	Weight kg
 <b>K00 0000L</b>    <b>K00 0000</b>  <b>K00 5000</b>  <b>K00 0000X</b>	<b>7 decimal</b>				
	Front	Multi-fixing		<b>K1C 027BL</b>	0.121
		By Ø 22 mm hole		<b>K1C 027B</b>	0.105
	Rear			<b>K1C 027BX</b> (2)	0.183
				<b>K1C 527B</b>	0.140
	<b>8 decimal</b>				
	Front	Multi-fixing		<b>K1D 028BL</b>	0.126
		By Ø 22 mm hole		<b>K1D 028B</b>	0.110
	Rear			<b>K1D 028BX</b> (2)	0.188
				<b>K1D 528B</b>	0.150
	<b>9 decimal</b>				
	Front	Multi-fixing		<b>K1D 029BL</b>	0.126
		By Ø 22 mm hole		<b>K1D 029B</b>	0.110
	Rear			<b>K1D 029BX</b> (2)	0.188
				<b>K1D 529B</b>	0.150
	<b>10 decimal</b>				
	Front	Multi-fixing		<b>K1D 030BL</b>	0.126
		By Ø 22 mm hole		<b>K1D 030B</b>	0.110
	Rear			<b>K1D 030BX</b> (2)	0.188
				<b>K1D 530B</b>	0.150
	<b>11 decimal</b>				
	Front	Multi-fixing		<b>K1D 031BL</b>	0.126
		By Ø 22 mm hole		<b>K1D 031B</b>	0.110
	Rear			<b>K1D 531B</b>	0.150
	<b>12 decimal</b>				
	Front	Multi-fixing		<b>K1D 032BL</b>	0.126
		By Ø 22 mm hole		<b>K1D 032B</b>	0.110
	Rear			<b>K1D 532B</b>	0.150

(1) *I*<sub>th</sub> = 12 A.  
(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAX Z1000**.

# Cam switches

Adaptable sub-assemblies, 12 and 20 A  
Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67

Paralleling switches with “0” position						
Wiring diagram	Switching programme	Switch position	Mounting method		Reference, to be completed (1)	Weight kg
1-pole for 2 loads						
			Front	Multi-fixing	<b>K●B 002GL</b>	0.101
				By Ø 22 mm hole	<b>K●B 002G</b>	0.085
					<b>K●B 002GX</b> (2)	0.163
			Rear		<b>K●B 502G</b>	0.125
1-pole for 3 loads						
			Front	Multi-fixing	<b>K●C 003GL</b>	0.121
				By Ø 22 mm hole	<b>K●C 003G</b>	0.105
					<b>K●C 003GX</b> (2)	0.183
			Rear		<b>K●C 503G</b>	0.140
1-pole for 4 loads						
			Front	Multi-fixing	<b>K●D 004GL</b>	0.126
				By Ø 22 mm hole	<b>K●D 004G</b>	0.110
					<b>K●D 004GX</b> (2)	0.188
			Rear		<b>K●D 504G</b>	0.150
2-pole for 2 loads						
			Front	Multi-fixing	<b>K●D 012GL</b>	0.126
				By Ø 22 mm hole	<b>K●D 012G</b>	0.110
					<b>K●D 012GX</b> (2)	0.188
			Rear		<b>K●D 512G</b>	0.150
2-pole for 3 loads						
			Front	Multi-fixing	<b>K●F 013GL</b>	0.156
				By Ø 22 mm hole	<b>K●F 013G</b>	0.140
					<b>K●F 013GX</b> (2)	0.218
			Rear		<b>K●F 513G</b>	0.175

(1) To order a cam switch with thermal current  $I_{th} = 12\text{ A}$ , replace the ● in the reference by 1.  
Example **K1B 002G**.  
To order a cam switch with thermal current  $I_{th} = 20\text{ A}$ , replace the ● in the reference by 2.  
Example **K2B 002G**.  
(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAX Z1●●●**.

# Cam switches

Adaptable sub-assemblies, 12 and 20 A  
Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67

Paralleling switches with “0” position (continued)

Wiring diagram	Switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
2-pole for 4 loads					
			Front Multi-fixing By Ø 22 mm hole	<b>K0H 014GL</b> <b>K0H 014G</b> <b>K0H 014GX</b> (2)	0.181 0.165 0.243
			Rear	<b>K0H 514G</b>	0.195
3-pole for 2 loads					
			Front Multi-fixing By Ø 22 mm hole	<b>K0F 022GL</b> <b>K0F 022G</b> <b>K0F 022GX</b> (2)	0.156 0.140 0.218
			Rear	<b>K0F 522G</b>	0.175
3-pole for 3 loads					
			Front Multi-fixing By Ø 22 mm hole	<b>K0I 023GL</b> <b>K0I 023G</b> <b>K0I 023GX</b> (2)	0.201 0.185 0.263
			Rear	<b>K0I 523G</b>	0.215
3-pole for 4 loads					
			Front Multi-fixing By Ø 22 mm hole	<b>K0M 024GL</b> <b>K0M 024G</b> <b>K0M 024GX</b> (2)	0.241 0.225 0.303
			Rear	<b>K0M 524G</b>	0.245











(1) To order a cam switch with thermal current Ith = 12 A, replace the ● in the reference by 1.  
Example K1H 014G.  
To order a cam switch with thermal current Ith = 20 A, replace the ● in the reference by 2.  
Example K2H 014G.  
(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAX Z1000.

# Cam switches

Adaptable sub-assemblies, 12 and 20 A  
Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67

## Stepping switches (2 to 11 step), single-pole, with “0” position









Wiring diagram and switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
 <i>K00 0000L</i>		Front	Multi-fixing	<b>K0B 002QL</b> 0.101
			By Ø 22 mm hole	<b>K0B 002Q</b> 0.085
		Rear		<b>K0B 002QX</b> (2) 0.163
				<b>K0B 502Q</b> 0.125
 <i>K00 0000</i>		Front	Multi-fixing	<b>K0C 003QL</b> 0.121
			By Ø 22 mm hole	<b>K0C 003Q</b> 0.105
		Rear		<b>K0C 003QX</b> (2) 0.183
				<b>K0C 503Q</b> 0.140
 <i>K00 5000</i>		Front	Multi-fixing	<b>K0D 004QL</b> 0.126
			By Ø 22 mm hole	<b>K0D 004Q</b> 0.110
		Rear		<b>K0D 004QX</b> (2) 0.188
				<b>K0D 504Q</b> 0.150
 <i>K00 5000</i>		Front	Multi-fixing	<b>K0E 005QL</b> 0.146
			By Ø 22 mm hole	<b>K0E 005Q</b> 0.130
		Rear		<b>K0E 005QX</b> (2) 0.208
				<b>K0E 505Q</b> 0.165
 <i>K00 0000X</i>		Front	Multi-fixing	<b>K0F 006QL</b> 0.156
			By Ø 22 mm hole	<b>K0F 006Q</b> 0.140
		Rear		<b>K0F 006QX</b> (2) 0.218
				<b>K0F 506Q</b> 0.175
 <i>K00 0000X</i>		Front	Multi-fixing	<b>K0G 007QL</b> 0.176
			By Ø 22 mm hole	<b>K0G 007Q</b> 0.160
		Rear		<b>K0G 007QX</b> (2) 0.238
				<b>K0G 507Q</b> 0.190

(1) To order a cam switch with thermal current  $I_{th} = 12\text{ A}$ , replace the ● in the reference by 1.  
Example **K1B 002Q**.  
To order a cam switch with thermal current  $I_{th} = 20\text{ A}$ , replace the ● in the reference by 2.  
Example **K2B 002Q**.  
(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAX Z1000**.

# Cam switches

Adaptable sub-assemblies, 12 and 20 AA  
Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67



















Stepping switches (2 to 11 step), single-pole, with "0" position (continued)					
Wiring diagram and switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg	
	8 step + "0"				
		Front	Multi-fixing	<b>K0H 008QL</b>	0.181
		By Ø 22 mm hole		<b>K0H 008Q</b>	0.165
				<b>K0H 008QX (2)</b>	0.243
		Rear		<b>K0H 508Q</b>	0.195
	9 step + "0"				
		Front	Multi-fixing	<b>K0I 009QL</b>	0.201
		By Ø 22 mm hole		<b>K0I 009Q</b>	0.185
				<b>K0I 009QX (2)</b>	0.263
		Rear		<b>K0I 509Q</b>	0.215
	10 step + "0"				
		Front	Multi-fixing	<b>K0K 010QL</b>	0.211
		By Ø 22 mm hole		<b>K0K 010Q</b>	0.195
				<b>K0K 010QX (2)</b>	0.273
		Rear		<b>K0K 510Q</b>	0.220
	11 step + "0"				
		Front	Multi-fixing	<b>K0L 011QL</b>	0.231
		By Ø 22 mm hole		<b>K0L 011Q</b>	0.215
				<b>K0L 011QX (2)</b>	0.293
		Rear		<b>K0L 511Q</b>	0.240

(1) To order a cam switch with thermal current Ith = 12 A, replace the ● in the reference by 1.  
Example **K1H 008Q**.  
To order a cam switch with thermal current Ith = 20 A, replace the ● in the reference by 2.  
Example **K2H 008Q**.  
(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAX Z1000**.

Cam switches  
Adaptable sub-assemblies, 12 and 20 A  
Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67

Stepping switches (2 to 12 step), single-pole, without “0” position

Wiring diagram and switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg	
      	<b>2 step</b>				
		Front	Multi-fixing	<b>K●B 002NL</b>	0.101
		By Ø 22 mm hole	<b>K●B 002N</b>	0.085	
				<b>K●B 002NX</b> (2)	0.163
		Rear		<b>K●B 502N</b>	0.125
	<b>3 step</b>				
		Front	Multi-fixing	<b>K●C 003NL</b>	0.121
		By Ø 22 mm hole	<b>K●C 003N</b>	0.105	
				<b>K●C 003NX</b> (2)	0.183
		Rear		<b>K●C 503N</b>	0.140
	<b>4 step</b>				
		Front	Multi-fixing	<b>K●D 004NL</b>	0.126
		By Ø 22 mm hole	<b>K●D 004N</b>	0.110	
				<b>K●D 004NX</b> (2)	0.188
		Rear		<b>K●D 504N</b>	0.150
	<b>5 step</b>				
		Front	Multi-fixing	<b>K●E 005NL</b>	0.146
		By Ø 22 mm hole	<b>K●E 005N</b>	0.130	
				<b>K●E 005NX</b> (2)	0.208
		Rear		<b>K●E 505N</b>	0.165
	<b>6 step</b>				
		Front	Multi-fixing	<b>K●F 006NL</b>	0.156
		By Ø 22 mm hole	<b>K●F 006N</b>	0.140	
				<b>K●F 006NX</b> (2)	0.218
		Rear		<b>K●F 506N</b>	0.175
	<b>7 step</b>				
		Front	Multi-fixing	<b>K●G 007NL</b>	0.176
		By Ø 22 mm hole	<b>K●G 007N</b>	0.160	
				<b>K●G 007NX</b> (2)	0.238
		Rear		<b>K●G 507N</b>	0.190
	<b>8 step</b>				
		Front	Multi-fixing	<b>K●H 008NL</b>	0.181
		By Ø 22 mm hole	<b>K●H 008N</b>	0.165	
				<b>K●H 008NX</b> (2)	0.243
		Rear		<b>K●H 508N</b>	0.195

(1) To order a cam switch with thermal current  $I_{th} = 12$  A, replace the ● in the reference by 1.

Example **K1B 002N**.

To order a cam switch with thermal current  $I_{th} = 20$  A, replace the ● in the reference by 2.

Example **K2B 002N**.









(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAX Z1●●●**.

# Cam switches

Adaptable sub-assemblies, 12 and 20 A  
Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67

## Stepping switches (2 to 12 step), single-pole, without “0” position (continued)

Wiring diagram and switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
 <b>K00 0000L</b>   <b>K00 0000</b>   <b>K00 5000</b>   <b>K00 0000X</b>	<b>9 step</b>			
		Front	Multi-fixing	<b>K00 009NL</b> 0.201
		By Ø 22 mm hole	<b>K00 009N</b>	0.185
			<b>K00 009NX</b> (2)	0.263
	Rear		<b>K00 509N</b>	0.215
	<b>10 step</b>			
		Front	Multi-fixing	<b>K00 010NL</b> 0.211
		By Ø 22 mm hole	<b>K00 010N</b>	0.195
			<b>K00 010NX</b> (2)	0.273
	Rear		<b>K00 510N</b>	0.220
	<b>11 step</b>			
		Front	Multi-fixing	<b>K00 011NL</b> 0.231
		By Ø 22 mm hole	<b>K00 011N</b>	0.215
			<b>K00 011NX</b> (2)	0.293
	Rear		<b>K00 511N</b>	0.240
	<b>12 step</b>			
		Front	Multi-fixing	<b>K00 021NL</b> 0.241
		By Ø 22 mm hole	<b>K00 021N</b>	0.225
			<b>K00 021NX</b> (2)	0.303
	Rear		<b>K00 521N</b>	0.245












(1) To order a cam switch with thermal current Ith = 12 A, replace the ● in the reference by 1.  
Example **K11 009N**.  
To order a cam switch with thermal current Ith = 20 A, replace the ● in the reference by 2.  
Example **K21 009N**.  
(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAX Z1000**.

# Cam switches

Adaptable sub-assemblies, 12 and 20 A  
Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67

## Stepping switches (2 to 6 step), 2-pole, with "0" position

Wiring diagram and switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
 <b>K00 0000L</b>   <b>K00 0000</b>   <b>K00 5000</b>  <b>K00 0000X</b>	<b>2 step + "0"</b> 	Front Multi-fixing By Ø 22 mm hole	<b>K0D 012QL</b> <b>K0D 012Q</b> <b>K0D 012QX</b> (2) <b>K0D 512Q</b>	0.126 0.110 0.188 0.150
	<b>3 step + "0"</b> 	Front Multi-fixing By Ø 22 mm hole	<b>K0F 013QL</b> <b>K0F 013Q</b> <b>K0F 013QX</b> (2) <b>K0F 513Q</b>	0.156 0.140 0.218 0.175
	<b>4 step + "0"</b> 	Front Multi-fixing By Ø 22 mm hole	<b>K0H 014QL</b> <b>K0H 014Q</b> <b>K0H 014QX</b> (2) <b>K0H 514Q</b>	0.181 0.165 0.243 0.195
	<b>5 step + "0"</b> 	Front Multi-fixing By Ø 22 mm hole	<b>K0K 015QL</b> <b>K0K 015Q</b> <b>K0K 015QX</b> (2) <b>K0K 515Q</b>	0.211 0.195 0.273 0.220
	<b>6 step + "0"</b> 	Front Multi-fixing By Ø 22 mm hole	<b>K0M 016QL</b> <b>K0M 016Q</b> <b>K0M 016QX</b> (2) <b>K0M 516Q</b>	0.241 0.225 0.303 0.245

(1) To order a cam switch with thermal current  $I_{th} = 12\text{ A}$ , replace the ● in the reference by 1.  
Example **K1D 012Q**.  
To order a cam switch with thermal current  $I_{th} = 20\text{ A}$ , replace the ● in the reference by 2.  
Example **K2D 012Q**.  
(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAX Z1000**.

Cam switches  
Adaptable sub-assemblies, 12 and 20 A  
Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67



K00 0000L



K00 0000



K00 5000



K00 0000X

Stepping switches (2 to 6 step), 2-pole, without "0" position					
Wiring diagram and switching programme	Switch position	Mounting method		Reference, to be completed (1)	Weight kg
	2 step				
	Front	Multi-fixing		K0D 012NL	0.126
		By Ø 22 mm hole		K0D 012N	0.110
	Rear			K0D 012NX (2)	0.188
				K0D 512N	0.150
	3 step				
	Front	Multi-fixing		K0F 013NL	0.156
		By Ø 22 mm hole		K0F 013N	0.140
	Rear			K0F 013NX (2)	0.218
				K0F 513N	0.175
	4 step				
	Front	Multi-fixing		K0H 014NL	0.181
		By Ø 22 mm hole		K0H 014N	0.165
	Rear			K0H 014NX (2)	0.243
				K0H 514N	0.195
	5 step				
	Front	Multi-fixing		K0K 015NL	0.211
		By Ø 22 mm hole		K0K 015N	0.195
	Rear			K0K 015NX (2)	0.273
				K0K 515N	0.220
	6 step				
	Front	Multi-fixing		K0M 016NL	0.241
		By Ø 22 mm hole		K0M 016N	0.225
	Rear			K0M 016NX (2)	0.303
				K0M 516N	0.245

(1) To order a cam switch with thermal current Ith = 12 A, replace the ● in the reference by 1.  
Example K1D 012N.  
To order a cam switch with thermal current Ith = 20 A, replace the ● in the reference by 2.  
Example K2D 012N.  
(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAX Z1●●●.
















## Cam switches

Adaptable sub-assemblies, 12 and 20 A

Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67

## Stepping switches (2 to 6 step), 3-pole, with "0" position

Wiring diagram	Switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
 K00 0000L		 2 step + "0"	Front Multi-fixing	K0F 022QL	0.156
			By Ø 22 mm hole	K0F 022Q K0F 022QX (2)	0.140 0.218
			Rear	K0F 522Q	0.175
 K00 0000		 3 step + "0"	Front Multi-fixing	K0I 023QL	0.201
			By Ø 22 mm hole	K0I 023Q K0I 023QX (2)	0.185 0.263
			Rear	K0I 523Q	0.215
 K00 0000		 4 step + "0"	Front Multi-fixing	K0M 024QL	0.241
			By Ø 22 mm hole	K0M 024Q K0M 024QX (2)	0.225 0.303
			Rear	K0M 524Q	0.245
 K00 5000		 5 step + "0"	Front Multi-fixing	K0P 025QL	0.286
			By Ø 22 mm hole	K0P 025Q K0P 025QX (2)	0.270 0.348
			Rear	K0P 525Q	0.285
 K00 0000X		 6 step + "0"	Front Multi-fixing	K0S 026QL	0.321
			By Ø 22 mm hole	K0S 026Q K0S 026QX (2)	0.305 0.383
			Rear	K0S 526Q	0.320

(1) To order a cam switch with thermal current  $I_{th} = 12$  A, replace the ● in the reference by 1.  
Example K1F 022Q.

To order a cam switch with thermal current  $I_{th} = 20$  A, replace the ● in the reference by 2.

Example K2F 022Q.

(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAX Z1000.





















## Cam switches

Adaptable sub-assemblies, 12 and 20 A

Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67

## Stepping switches (2 to 6 step), 3-pole, without "0" position

	Wiring diagram	Switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
 <b>K00 0000L</b>			<b>2 step</b> 	Front Multi-fixing By Ø 22 mm hole	<b>K0F 022NL</b> <b>K0F 022N</b> <b>K0F 022NX</b> (2)	0.156 0.140 0.218
				Rear	<b>K0F 522N</b>	0.175
 <b>K00 0000</b>			<b>3 step</b> 	Front Multi-fixing By Ø 22 mm hole	<b>K0I 023NL</b> <b>K0I 023N</b> <b>K0I 023NX</b> (2)	0.201 0.185 0.263
				Rear	<b>K0I 523N</b>	0.215
 <b>K00 0000</b>			<b>4 step</b> 	Front Multi-fixing By Ø 22 mm hole	<b>K0M 024NL</b> <b>K0M 024N</b> <b>K0M 024NX</b> (2)	0.241 0.225 0.303
				Rear	<b>K0M 524N</b>	0.245
 <b>K00 5000</b>			<b>5 step</b> 	Front Multi-fixing By Ø 22 mm hole	<b>K0P 025NL</b> <b>K0P 025N</b> <b>K0P 025NX</b> (2)	0.286 0.270 0.348
				Rear	<b>K0P 525N</b>	0.285
 <b>K00 0000X</b>			<b>6 step</b> 	Front Multi-fixing By Ø 22 mm hole	<b>K0S 026NL</b> <b>K0S 026N</b> <b>K0S 026NX</b> (2)	0.321 0.305 0.383
				Rear	<b>K0S 526N</b>	0.320

(1) To order a cam switch with thermal current  $I_{th} = 12$  A, replace the ● in the reference by 1.  
Example K1F 022N.

To order a cam switch with thermal current  $I_{th} = 20$  A, replace the ● in the reference by 2.  
Example K2F 022N.

(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAX Z1000.













## Cam switches

Adaptable sub-assemblies, 12 and 20 A

Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67

## Stepping switches (2 to 5 step), 4-pole, with "0" position

Wiring diagram	Switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
 K00 0000L			Front	Multi-fixing	K0H 032QL 0.181
			By Ø 22 mm hole	K0H 032Q 0.165	
				K0H 032QX (2) 0.200	
			Rear	K0H 532Q 0.195	
 K00 0000			Front	Multi-fixing	K0M 033QL 0.241
			By Ø 22 mm hole	K0M 033Q 0.225	
			Rear	K0M 533Q 0.245	
 K00 5000			Front	Multi-fixing	K0Q 034QL 0.296
			By Ø 22 mm hole	K0Q 034Q 0.280	
			Rear	K0Q 534Q 0.295	
 K00 0000X			Front	Multi-fixing	K0U 035QL 0.351
			By Ø 22 mm hole	K0U 035Q 0.335	
			Rear	K0U 535Q 0.345	

(1) To order a cam switch with thermal current  $I_{th} = 12$  A, replace the ● in the reference by 1.

Example K1H 032Q.













To order a cam switch with thermal current  $I_{th} = 20$  A, replace the ● in the reference by 2.

Example K2H 032Q.

(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAX Z1000.

Cam switches  
Adaptable sub-assemblies, 12 and 20 A  
Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67

Stepping switches (2 to 5 step), 4-pole, without "0" position						
Wiring diagram	Switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg	
 <b>K●● 0●●●L</b>			Front	Multi-fixing	<b>K●H 032NL</b> 0.181	
			Rear	By Ø 22 mm hole	<b>K●H 032N</b> 0.165	
					<b>K●H 032NX</b> (2) 0.200	
 <b>K●● 0●●●</b>			Front	Multi-fixing	<b>K●M 033NL</b> 0.241	
			Rear	By Ø 22 mm hole	<b>K●M 033N</b> 0.225	
					<b>K●M 533N</b> 0.245	
 <b>K●● 5●●●</b>			Front	Multi-fixing	<b>K●Q 034NL</b> 0.296	
			Rear	By Ø 22 mm hole	<b>K●Q 034N</b> 0.280	
					<b>K●Q 534N</b> 0.295	
 <b>K●● 0●●●X</b>			Front	Multi-fixing	<b>K●U 035NL</b> 0.351	
			Rear	By Ø 22 mm hole	<b>K●U 035N</b> 0.335	
					<b>K●U 535N</b> 0.345	




(1) To order a cam switch with thermal current Ith = 12 A, replace the ● in the reference by 1.  
Example **K1H 032N**.  
To order a cam switch with thermal current Ith = 20 A, replace the ● in the reference by 2.  
Example **K2H 032N**.  
(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAX Z1●●●**.

# Cam switches

Adaptable sub-assemblies, 12 and 20 A  
Bodies (contact blocks + fixing plate)




To combine with operating heads: see pages 3/66 and 3/67

## Ammeter switches with "0" position

Wiring diagram	Switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
For 3 circuits					
			Front	Multi-fixing	<b>KoF 003ML</b> 0.156
			By Ø 22 mm hole	<b>KoF 003M</b>	0.140
				<b>KoF 003MX (2)</b>	0.218
				<b>KoF 503M</b>	0.175






KoF 0000L

For 4 circuits					
			Front	Multi-fixing	<b>KoH 004ML</b> 0.181
			By Ø 22 mm hole	<b>KoH 004M</b>	0.165
				<b>KoH 004MX (2)</b>	0.243
				<b>KoH 504M</b>	0.195






KoH 0000

## Ammeter switches without "0" position

Wiring diagram	Switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
For 3 circuits					
			Front	Multi-fixing	<b>KoF 013ML</b> 0.156
			By Ø 22 mm hole	<b>KoF 013M</b>	0.140
				<b>KoF 013MX (2)</b>	0.218
				<b>KoF 513M</b>	0.175



KoF 5000

For 4 circuits					
			Front	Multi-fixing	<b>KoH 014ML</b> 0.181
			By Ø 22 mm hole	<b>KoH 014M</b>	0.165
				<b>KoH 014MX (2)</b>	0.243
				<b>KoH 514M</b>	0.195



KoH 0000X

- (1) To order a cam switch with thermal current  $I_{th} = 12$  A, replace the ● in the reference by 1.  
Example **K1F 003M**.  
To order a cam switch with thermal current  $I_{th} = 20$  A, replace the ● in the reference by 2.  
Example **K2F 003M**.
- (2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAX Z1000**.

## Cam switches

Adaptable sub-assemblies, 12 and 20 A

Bodies (contact blocks + fixing plate)




To combine with operating heads: see pages 3/66 and 3/67

## Voltmeter switches

Wiring diagram	Switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
----------------	---------------------	-----------------	-----------------	--------------------------------	-----------



## For measurements between 3 phases and neutral

## With "0" position



Front	Multi-fixing	K0D 023ML	0.126
	By Ø 22 mm hole	K0D 023M	0.110
		K0D 023MX (2)	0.188
Rear		K0D 523M	0.150

## Without "0" position






Front	Multi-fixing	K0D 033ML	0.126
	By Ø 22 mm hole	K0D 033M	0.110
		K0D 533M	0.150



## For measurements between 3 phases



## With "0" position

K00 0000



Front	Multi-fixing	K0D 024ML	0.126
	By Ø 22 mm hole	K0D 024M	0.110
		K0D 024MX (2)	0.188
Rear		K0D 524M	0.150

## Without "0" position






Front	Multi-fixing	K0D 034ML	0.126
	By Ø 22 mm hole	K0D 034M	0.110
Rear		K0D 534M	0.150



## For measurements between 3 phases and between 1 phase and neutral



## With "0" position

K00 5000



Front	Multi-fixing	K0E 025ML	0.146
	By Ø 22 mm hole	K0E 025M	0.130
		K0E 025MX (2)	0.208
Rear		K0E 525M	0.165

## Without "0" position



Front	Multi-fixing	K0E 035ML	0.146
	By Ø 22 mm hole	K0E 035M	0.130
		K0E 535M	0.165



(1) To order a cam switch with thermal current  $I_{th} = 12$  A, replace the ● in the reference by 1.

Example **K1D 023M**.

To order a cam switch with thermal current  $I_{th} = 20$  A, replace the ● in the reference by 2.

Example **K2D 023M**.

(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAX Z1000**.

# Cam switches

Adaptable sub-assemblies, 12 and 20 A  
Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67


Voltmeter switches (continued)

Wiring diagram	Switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
----------------	---------------------	-----------------	-----------------	--------------------------------	-----------


For measurements between 3 phases of 2 supplies



K00 0000L





With "0" position



Front	Multi-fixing	K0H 026ML	0.181
	By Ø 22 mm hole	K0H 026M	0.165

Rear		K0H 526M	0.195
------	--	----------	-------

Without "0" position



Front	Multi-fixing	K0H 036ML	0.181
	By Ø 22 mm hole	K0H 036M	0.165


Rear		K0H 536M	0.195
------	--	----------	-------



K00 0000


For measurements between 3 phases and between each of the 3 phases and neutral

With "0" position





Front	Multi-fixing	K0F 027ML	0.156
	By Ø 22 mm hole	K0F 027M	0.140

Rear		K0F 527M	0.175
------	--	----------	-------



Without "0" position



Front	Multi-fixing	K0F 037ML	0.156
	By Ø 22 mm hole	K0F 037M	0.140

Rear		K0F 537M	0.175
------	--	----------	-------



K00 5000



K00 0000X

(1) To order a cam switch with thermal current  $I_{th} = 12$  A, replace the ● in the reference by 1.

Example K1H 026M.

To order a cam switch with thermal current  $I_{th} = 20$  A, replace the ● in the reference by 2.

Example K2H 026M.

(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAX Z1000.

## Cam switches

Adaptable sub-assemblies, 12 and 20 A

Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67

## Stepping switches (2 and 3 step), with "0" position + left-hand position

Wiring diagram	Switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
			1-pole: 2 step to right + 1 step to left		
			Front	Multi-fixing	K0C 002LL 0.121
				By Ø 22 mm hole	K0C 002L 0.105
					K0C 002LX (2) 0.183
			Rear		K0C 502L 0.140
			1-pole: 3 step to right + 1 step to left		
			Front	Multi-fixing	K0D 003LL 0.126
				By Ø 22 mm hole	K0D 003L 0.110
					K0D 003LX (2) 0.188
			Rear		K0D 503L 0.150
			2-pole: 2 step to right + 1 step to left		
			Front	Multi-fixing	K0F 012LL 0.156
				By Ø 22 mm hole	K0F 012L 0.140
					K0F 012LX (2) 0.218
			Rear		K0F 512L 0.175
			2-pole: 3 step to right + 1 step to left		
			Front	Multi-fixing	K0H 013LL 0.181
				By Ø 22 mm hole	K0H 013L 0.165
					K0H 013LX 0.243
			Rear		K0H 513L 0.195
			3-pole: 2 step to right + 1 step to left		
			Front	Multi-fixing	K0I 022LL 0.201
				By Ø 22 mm hole	K0I 022L 0.185
			Rear		K0I 522L 0.210
			3-pole: 3 step to right + 1 step to left		
			Front	Multi-fixing	K0M 023LL 0.241
				By Ø 22 mm hole	K0M 023L 0.225
			Rear		K0M 523L 0.245

(1) To order a cam switch with thermal current  $I_{th} = 12$  A, replace the ● in the reference by 1.

Example **K1C 002L**.

To order a cam switch with thermal current  $I_{th} = 20$  A, replace the ● in the reference by 2.

Example **K2C 002L**.

(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAX Z1000**.

## Cam switches

Adaptable sub-assemblies, 12 and 20 A

Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67

## Multi-circuit switches

Wiring diagram	Switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
1-pole					
			Front	Multi-fixing By Ø 22 mm hole	<b>K●B 001SL</b> 0.101 <b>K●B 001S</b> 0.085 <b>K●B 001SX</b> (2) 0.163
			Rear	<b>K●B 501S</b>	0.125
2-pole					
			Front	Multi-fixing By Ø 22 mm hole	<b>K●D 002SL</b> 0.126 <b>K●D 002S</b> 0.110 <b>K●D 002SX</b> (2) 0.188
			Rear	<b>K●D 502S</b>	0.150
3-pole					
			Front	Multi-fixing By Ø 22 mm hole	<b>K●F 003SL</b> 0.156 <b>K●F 003S</b> 0.140 <b>K●F 003SX</b> (2) 0.218
			Rear	<b>K●F 503S</b>	0.175
4-pole					
			Front	Multi-fixing By Ø 22 mm hole	<b>K●H 004SL</b> 0.181 <b>K●H 004S</b> 0.165
			Rear	<b>K●H 504S</b>	0.195
5-pole					
			Front	Multi-fixing By Ø 22 mm hole	<b>K●K 005SL</b> 0.211 <b>K●K 005S</b> 0.195
			Rear	<b>K●K 505S</b>	0.220

(1) To order a cam switch with thermal current  $I_{th} = 12$  A, replace the ● in the reference by 1.

Example **K1F 003S**.

To order a cam switch with thermal current  $I_{th} = 20$  A, replace the ● in the reference by 2.

Example **K2F 003S**.

(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAX Z1●●●**.

K●● 0●●●L

K●● 0●●●

K●● 5●●●

K●● 0●●●X

Cam switches

Adaptable sub-assemblies, 12 and 20 A  
Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67

Reversing switches with “0” position

Wiring diagram	Switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
2-pole					
			Front Multi-fixing	<b>K●D 002WL</b>	0.126
			By Ø 22 mm hole	<b>K●D 002W</b>	0.110
				<b>K●D 002WX</b> (2)	0.188
			Rear	<b>K●D 502W</b>	0.150



K●● 0●●●L

3-pole					
			Front Multi-fixing	<b>K●E 003WL</b>	0.146
			By Ø 22 mm hole	<b>K●E 003W</b>	0.130
				<b>K●E 003WX</b> (2)	0.208
			Rear	<b>K●E 503W</b>	0.165



K●● 0●●●

Reversing switches with spring return from 330° and from 30° to “0” position

Wiring diagram	Switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
2-pole					
			Front Multi-fixing	<b>K●D 022WL</b>	0.126
			By Ø 22 mm hole	<b>K●D 022W</b>	0.110
				<b>K●D 022WX</b> (2)	0.188
			Rear	<b>K●D 522W</b>	0.150



K●● 5●●●

3-pole					
			Front Multi-fixing	<b>K●E 023WL</b>	0.146
			By Ø 22 mm hole	<b>K●E 023W</b>	0.130
				<b>K●E 023WX</b> (2)	0.208
			Rear	<b>K●E 523W</b>	0.165



K●● 0●●●X

(1) To order a cam switch with thermal current  $I_{th} = 12$  A, replace the ● in the reference by 1.  
Example **K1D 002W**.  
To order a cam switch with thermal current  $I_{th} = 20$  A, replace the ● in the reference by 2.  
Example **K2D 002W**.  
(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAX Z1●●●**.

# Cam switches

Adaptable sub-assemblies, 12 A  
Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67

3



K00 0000L

Star-delta switches					
Wiring diagram	Switching programme	Switch position	Mounting method	Reference (1)	Weight kg
			Front Multi-fixing	K2H 001YL	0.181
			By Ø 22 mm hole	K2H 001Y	0.165
				K2H 001YX (2)	0.243
			Rear	K2H 501Y	0.195



K2G 0000

With slave contact, without supply disconnection					
Wiring diagram	Switching programme	Switch position	Mounting method	Reference (1)	Weight kg
			Front Multi-fixing	K2G 003YL	0.176
			By Ø 22 mm hole	K2G 003Y	0.160
				K2G 003YX (2)	0.238
			Rear	K2G 503Y	0.190



K2K 5000

With slave contact, with supply disconnection					
Wiring diagram	Switching programme	Switch position	Mounting method	Reference (1)	Weight kg
			Front Multi-fixing	K2K 004YL	0.211
			By Ø 22 mm hole	K2K 004Y	0.195
				K2K 004YX (2)	0.273
			Rear	K2K 504Y	0.220



K2K 0000X

Reversing star-delta switches					
Wiring diagram	Switching programme	Switch position	Mounting method	Reference (1)	Weight kg
Without slave contact					
			Front Multi-fixing	K2K 006YL	0.211
			By Ø 22 mm hole	K2K 006Y	0.195
			Rear	K2K 506Y	0.220

(1) Ith = 20 A.  
(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAX Z1000.

## Cam switches

Adaptable sub-assemblies, 12 and 20 A

Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67

3



## Reversing star-delta switches (continued)

Wiring diagram	Switching programme	Switch position	Mounting method	Reference (2)	Weight kg
----------------	---------------------	-----------------	-----------------	---------------	-----------

## With slave contact



K2M 0000L



Front	Multi-fixing	K2M 007YL	0.241
	By Ø 22 mm hole	K2M 007Y	0.225
Rear		K2M 507Y	0.245


## Pole change switches for 2-speed motors

Wiring diagram	Switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
----------------	---------------------	-----------------	-----------------	--------------------------------	-----------

## For motors with 2 separate windings



K2F 0000





Front	Multi-fixing	K2F 001PL	0.156
	By Ø 22 mm hole	K2F 001P	0.140
		K2F 001PX (3)	0.218
Rear		K2F 501P	0.175

## For motors with 2 separate windings, with centre "0" position



K2F 5000




Front	Multi-fixing	K2F 002PL	0.156
	By Ø 22 mm hole	K2F 002P	0.140
		K2F 002PX (3)	0.218
Rear		K2F 502P	0.175

## For motors with tapped "Dahlander" windings



K2H 0000X



Front	Multi-fixing	K2H 004PL	0.181
	By Ø 22 mm hole	K2H 004P	0.165
		K2H 004PX (3)	0.243
Rear		K2H 504P	0.195

(1) To order a cam switch with thermal current  $I_{th} = 12$  A, replace the ● in the reference by 1.

Example K1F 001P.

To order a cam switch with thermal current  $I_{th} = 20$  A, replace the ● in the reference by 2.

Example K2F 001P.

(2)  $I_{th} = 20$  A.

(3) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type KAX Z1000.

# Cam switches

Adaptable sub-assemblies, 12 and 20 A  
Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67

Pole change switches for 2-speed motors (continued)

Wiring diagram	Switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
For motors with tapped "Dahlander" windings, with centre "0" position					
			Front Multi-fixing	<b>K●H 005PL</b>	0.181
			By Ø 22 mm hole	<b>K●H 005P</b>	0.165
				<b>K●H 005PX</b> (2)	0.243
			Rear	<b>K●H 505P</b>	0.195



K●● 0●●●L

Reversing pole change switches for 2-speed motors

Wiring diagram	Switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
For motors with 2 separate windings, with centre "0" position					
			Front Multi-fixing	<b>K●K 008PL</b>	0.211
			By Ø 22 mm hole	<b>K●K 008P</b>	0.195
			Rear	<b>K●K 508P</b>	0.220



K●● 0●●●



K●● 5●●●

For motors with tapped "Dahlander" windings, with centre "0" position

			Front Multi-fixing	<b>K●M 009PL</b>	0.241
			By Ø 22 mm hole	<b>K●M 009P</b>	0.225
			Rear	<b>K●M 509P</b>	0.245












K●● 0●●●X

(1) To order a cam switch with thermal current Ith = 12 A, replace the ● in the reference by 1.  
Example **K1H 005P**.  
To order a cam switch with thermal current Ith = 20 A, replace the ● in the reference by 2.  
Example **K2H 005P**.  
(2) Bodies using the Ø 22 mm hole mounting method that can be fitted with chromium plated metal bezel operating heads, type **KAX Z1●●●**.

# Cam switches

Adaptable sub-assemblies, 12 and 20 A  
Bodies (contact blocks + fixing plate)

To combine with operating heads: see pages 3/66 and 3/67

Pole change switches for 3-speed motors					
Wiring diagram	Switching programme	Switch position	Mounting method	Reference, to be completed (1)	Weight kg
For motors with open tapped "Dahlander" winding and separate winding for low speed					
			Front	Multi-fixing	0.231
				By Ø 22 mm hole	0.215
			Rear		0.240
For motors with open tapped "Dahlander" winding and separate winding for intermediate speed					
			Front	Multi-fixing	0.231
				By Ø 22 mm hole	0.215
			Rear		0.240
For motors with open tapped "Dahlander" winding and separate winding for high speed					
			Front	Multi-fixing	0.231
				By Ø 22 mm hole	0.215
			Rear		0.240



K00 0000L



K00 0000



K00 5000



K00 0000X

(1) To order a cam switch with thermal current Ith = 12 A, replace the ● in the reference by 1.  
Example K1L 010P.  
To order a cam switch with thermal current Ith = 20 A, replace the ● in the reference by 2.  
Example K2L 010P.

# Cam switches

Adaptable sub-assemblies, 12 and 20 A  
Operating heads

To combine with bodies: see pages 3/34 to 3/65



KBG 3H



KCG 3Y



KAC 1H



KCC 1Y




KBC 1







KBD 1H

## Heads for "multi-fixing" front mounting bodies

Description	Switching angle and marking	Type of operator	Background colour of legend	Padlocking device	Reference	Weight kg
<b>With 45 x 45 mm front plate and handle</b>						
With blank legend (for engraving by user)	—	Black handle L = 35 mm	Matt black	Without	<b>KAG 3H</b>	0.012
			Metallic	Without	<b>KBG 3H</b>	0.012
With marked legend	90° 	Red handle L = 35 mm	Yellow	Without	<b>KCG 3H</b>	0.012
				With	<b>KCG 3Y</b>	0.024
Without legend (1)	—	Black handle L = 35 mm	—	Without	<b>KDG 3H</b>	0.010
		Red handle L = 35 mm	—	With	<b>KDG 3Y</b>	0.022


## Heads for Ø 22 mm hole, front mounting bodies

Description	Switching angle and marking	Type of operator	Background colour of legend	Padlocking device	Reference	Weight kg
<b>With 45 x 45 mm front plate and handle</b>						
With blank legend (for engraving by user)	—	Black handle L = 35 mm	Matt black	Without	<b>KAC 1H</b>	0.048
			Metallic	Without	<b>KBC 1H</b>	0.048
With marked legend	45° 	Black handle L = 35 mm	Matt black	Without	<b>KAC 1H41</b>	0.012
			Metallic	Without	<b>KBC 1H41</b>	0.012
	45° 	Black handle L = 35 mm	Matt black	Without	<b>KAC 1H48</b>	0.012
			Metallic	Without	<b>KBC 1H48</b>	0.012
	60° 	Black handle L = 35 mm	Matt black	Without	<b>KAC 1H61</b>	0.048
			Metallic	Without	<b>KBC 1H61</b>	0.048
	90° 	Red handle L = 35 mm	Yellow	Without	<b>KCC 1LH</b>	0.048
				With	<b>KCC 1Y</b>	0.060
Without legend (1)	—	Black handle L = 35 mm	—	Without	<b>KDC 1H</b>	0.046
		Red handle L = 35 mm	—	Without	<b>KDC 1LH</b>	0.046

## With 45 x 45 mm front plate and key operator (2)

With blank legend (for engraving by user)	45° and 90°	Key (2)	Matt black	Without	<b>KAC 1S</b>	0.063
			Metallic	Without	<b>KBC 1S</b>	0.063
	60°	Key (2)	Matt black	Without	<b>KAC 1Z</b>	0.063
			Metallic	Without	<b>KBC 1Z</b>	0.063
Without legend (1)	45° and 90°	Key (2)	—	Without	<b>KDC 1S</b>	0.061
	60°	Key (2)	—	Without	<b>KDC 1Z</b>	0.061

## With 60 x 60 mm front plate and handle

With blank legend (for engraving by user)	—	Black handle L = 42 mm	Matt black	Without	<b>KAD 1H</b>	0.053
			Metallic	Without	<b>KBD 1H</b>	0.053
With marked legend	90° 	Red handle L = 42 mm	Yellow	Without	<b>KCD 1MH</b>	0.053
Without legend (1)	—	Black handle L = 42 mm	—	Without	<b>KDD 1H</b>	0.053

(1) For separate marked legend ordering information, see pages 3/68 to 3/71.

(2) Head supplied with "Ronis" 8R 1 key. To order a head with a "Ronis" 455 key, add the suffix **R** to the references listed above.  
Example: reference for Ø 22 mm hole, front mounting 45 x 45 mm operating head with 45° switching angle and matt black legend, becomes **KAC 1SR**. For a head with "Ronis" 8R15 key, use the suffix **R1**.

## Cam switches

Adaptable sub-assemblies, 12 and 20 A  
Operating heads

To combine with bodies: see pages 3/34 to 3/65



KBD 1●



KBA 1H



KBA 1●



KAX Z1C12



KBE 1H

## Heads for Ø 22 mm hole, front mounting bodies (continued)

Description	Switching angle and marking	Type of operator	Background colour of legend	Padlocking device	Reference	Weight kg
<b>With 60 x 60 mm front plate and key operator (1)</b>						
With blank legend (to be engraved by user)	45° and 90°	Key (1)	Matt black	Without	KAD 1S	0.068
			Metallic	Without	KBD 1S	0.068
	60°	Key (1)	Matt black	Without	KAD 1Z	0.068
			Metallic	Without	KBD 1Z	0.068
Without legend (2)	45° and 90°	Key (1)	—	Without	KDD 1S	0.066
	60°	Key (1)	—	Without	KDD 1Z	0.066

## With Ø 29 mm, metallic finish, plastic bezel and handle or key operator (1)

Description	Switching angle and marking	Type of operator	Colour of bezel	Padlocking device	Reference	Weight kg
Circular heads	—	Black handle L = 35 mm	Matt black	Without	KAA 1H	0.042
			Metallic	Without	KBA 1H	0.042
	45°	Key (1)	Matt black	Without	KAA 1S	0.057
			Metallic	Without	KBA 1S	0.057
	60°	Key (1)	Matt black	Without	KAA 1Z	0.057
			Metallic	Without	KBA 1Z	0.057

## With Ø 38 mm, black, plastic bezel and handle

Circular head	—	Black handle L = 35 mm	Matt black	Without	KAA 2H	0.048
---------------	---	------------------------	------------	---------	--------	-------

## With Ø 28.5 mm chromium plated, metal bezel (3) (2) and standard, handle, long handle or key operator (4)

Circular heads	—	Standard black handle	Metal	Without	KAX Z1M12	0.040
		Standard red handle	Metal	Without	KAX Z1M14	0.040
		Long black handle	Metal	Without	KAX Z1C12	0.040
		Long red handle	Metal	Without	KAX Z1C14	0.040
	30°	Key	Metal	Without	KAX Z1S13● (4)	0.065
	45°	Key	Metal	Without	KAX Z1S14● (4)	0.065
	60°	Key	Metal	Without	KAX Z1S16● (4)	0.065
	90°	Key	Metal	Without	KAX Z1S19● (4)	0.065

## Operating heads for 4 hole, rear mounting bodies

Description	Switching angle and marking	Type of operator	Background colour of legend	Padlocking device	Reference	Weight kg
<b>With 45 x 45 mm front plate and handle</b>						
With blank legend (to be engraved by user)	—	Black handle L = 35 mm	Matt black	Without	KAE 1H	0.029
			Metallic	Without	KBE 1H	0.029
With marked legend	90°	Red handle L = 35 mm	Yellow	Without	KCE 1LH	0.029
				With	KCE 1Y	0.060

Without legend (2)	—	Black handle L = 35 mm	—	Without	KDE 1H	0.027
		Red handle L = 35 mm	—	Without	KDE 1LH	0.027

## With 60 x 60 mm front plate and handle

With blank legend (to be engraved by user)	—	Black handle L = 42 mm	Matt black	Without	KAF 1H	0.068
			Metallic	Without	KBF 1H	0.068
With marked legend	90°	Red handle L = 42 mm	Yellow	Without	KCF 1MH	0.068
Without legend (2)	—	Black handle L = 42 mm	—	Without	KDF 1H	0.066

(1) Head supplied with "Ronis" 8R1 key. To order a head with a "Ronis" 455 key, add the suffix **R** to the references listed above.Example: reference for operating head with 60 x 60 mm front plate, key operator, blank legend, 45° switching angle and matt black background, becomes **KAD 1SR**. For a head with "Ronis" 8R15 key, use the suffix **R1**.

(2) For separate marked legend ordering information, see pages 3/68 to 3/71.

(3) Heads **only** for use with bodies **K●●●●●X**, incorporating adaptor plate **KZ 127**. See pages 3/34 to 3/65.

(4) To order:

- a head with key n° 455, replace the ● in the reference by **1**. Example: **KAX Z1S131**,- a head with key n° 421, replace the ● in the reference by **2**. Example: **KAX Z1S132**,- a head with key n° 520, replace the ● in the reference by **3**. Example: **KAX Z1S133**,- a head with a special key, replace the ● in the reference by **9**. Example: **KAX Z1S139** (state the key number on the order).

Key withdrawal from all positions.

Cam switches

Adaptable sub-assemblies, 12 and 20 A  
Legends for **MULTI-FIXING** heads

45 x 45 mm legends - marked (1)

White text on black background

30°

KZ 18032L



KZ 18033L



KZ 18312L



45°

KZ 18041L



KZ 18042L



KZ 18043L



KZ 18044L



KZ 18045L



KZ 18046L



KZ 18047L



KZ 18048L



KZ 18412L



KZ 18413L



KZ 18415L



KZ 18416L



KZ 18417L



KZ 18418L



KZ 18419L



KZ 18420L



KZ 18421L



KZ 18422FL



KZ 18423FL



KZ 18434L



KZ 18436FL



KZ 18451L



60°

KZ 18061L



KZ 18630L



KZ 18631L



KZ 18632L



KZ 18634L



KZ 18635L



KZ 18637L



KZ 18068L



90°

KZ 18091L



KZ 18093L



KZ 18913L



KZ 18931FL



Black text on yellow background

45°

KZ 19041L



90°

KZ 19093L



KZ 19098FL



KZ 19910L



45 x 45 mm legends - unmarked

Colour	Sold in lots of	Unit reference	Weight kg
Black	20	KZ 17L	0.003
Metallic	20	KZ 18L	0.003
Yellow	10	KZ 19L	0.003

(1) Weight = 0.003 kg.


# Cam switches

Adaptable sub-assemblies, 12 and 20 A  
Legends for  $\varnothing 22$  mm HOLE mounting heads with plastic bezel


## 45 x 45 mm legends - marked (1)

Black text on metallic background


30°




45°



60°




90°



Black text on yellow background

45°



90°




## 45 x 45 mm legends - unmarked

Colour	Sold in lots of	Unit reference	Weight kg
Black	20	KZ 17	0.003
Metallic	20	KZ 18	0.003
Yellow	10	KZ 19	0.003


## 60 x 60 mm legends - marked (2)

Black text on metallic background


45°



60°



90°



## 60 x 60 mm legends - unmarked

Colour	Sold in lots of	Unit reference	Weight kg
Black	20	KZ 20	0.005
Metallic	20	KZ 21	0.005
Yellow	10	KZ 22	0.005

(1) Weight = 0.003 kg.

(2) Weight = 0.005 kg.

Cam switches

Adaptable sub-assemblies, 12 and 20 A  
Legends for Ø 22 mm HOLE mounting heads  
with chromium plated metal bezel, type KAX Z1●●●

46 x 46 mm - marked (PVC) (1)

White text on black background

30°

XBC Y7226	XBC Y7227	XBC Y7228	XBC Y7229	XBC Y7236	XBC Y2250	XBC Y7238	XBC Y7239

45°

XBC Y7220	XBC Y7221	XBC Y7222	XBC Y7223	XBC Y7224	XBC Y7225	XBC Y7230	XBC Y7231	XBC Y7232	XBC Y7233
XBC Y7234	XBC Y7235	XBC Y2213	XBC Y2214	XBC Y2215	XBC Y2216	XBC Y7217	XBC Y7251		

60°

XBC Y7212	XBC Y7240	XBC Y7241	XBC Y7242	XBC Y7243	XBC Y7268	XBC Y7168	XBC Y7064

90°

XBC Y2211	XBC Y2218	XBC Y2219


46 x 46 mm legends - unmarked (PVC)

Colour	Sold in lots of	Unit reference	Weight kg
Black/red	10	KZ 17X	0.004
White/yellow	10	KZ 19X	0.004


(1) Weight = 0.004 kg.

# Cam switches


Adaptable sub-assemblies, 12 and 20 A  
Legend holders for heads



KZ 13




KZ 15



KZ 01R




KZ 2



KZ 14

KZ 76



KZ 16

KZ 77

## Legend holders with and without legend

Description	For use with heads	Legend marking	Sold in lots of	Unit reference	Weight kg
With blank legend	With 45 x 45 mm front plate (1)	–	5	KZ 13	0.004
	With 60 x 60 mm front plate (1)	–	5	KZ 15	0.010
	Circular, with Ø 29 mm collar	–	5	KZ 01R ▲	0.010
With marked legend	Circular, with Ø 29 mm collar	1 2	1	KZ 1	0.003
		2 0 1	5	KZ 2	0.003
Without legend	With 45 x 45 mm front plate (1)	–	20	KZ 14	0.003
	With 60 x 60 mm front plate (1)	–	10	KZ 16	0.007

## Blank legends (for engraving) for legend holders

Description	For use with heads	Sold in lots of	Unit reference	Weight kg
<b>Legend for legend holder KZ 14</b> Plastic with metallic finish. Self-adhesive. For engraved markings.	With 45 x 45 mm front plate (1)	20	KZ 76	0.002
<b>Legend for legend holder KZ 16</b> Plastic with metallic finish. Self-adhesive. For engraved markings.	With 60 x 60 mm front plate (1)	10	KZ 77	0.003

(1) Operating heads for single Ø 22 mm hole or 4 hole mounting.


▲ Available: 1<sup>st</sup> quarter 2005.

# Cam switches


Complete switches, 12 and 20 A  
Separate components and accessories




KZ 27H




KZ 27




KZ 32




KZ 83



KZ 127



KZ 140



KZ 141


## Handles

Description	Colour	Dimensions	Sold in lots of	Unit reference	Weight
		mm			kg
New shape	Black	35	5	KZ 27H	0.007
		42	5	KZ 28H	0.009
	Red	35	5	KZ 41H	0.007
		42	5	KZ 42H	0.009
Old shape	Black	34	5	KZ 27	0.007
		42	5	KZ 28	0.009


## Accessories

Description	For use with	Dimensions	Sold in lots of	Unit reference	Weight
		mm			kg
Door interlocking plate	Rear mounting switches	45 x 45	5	KZ 32	0.010
Plate with rubber seal	Rear mounting switches. IP 65 between front plate and operating head	60 x 60	5	KZ 83	0.018
Adaptor plate, metal (replacement)	Mounting KAX Z1●●● chromium plated metal bezel heads on front mounting bodies for Ø 22 mm hole	—	1	KZ 127	0.088
Plastic plate (replacement)	Ø 22 mm hole, front mounting, clip-in bodies	—	1	KZ 140	0.010
Multi-fixing plate (replacement)	"Multi-fixing", front mounting, — bodies	—	1	KZ 141	0.026


## Cam switches

Complete switches, 12 and 20 A  
Separate components and accessories


KZ 6●



KZ 5●



KZ 3●




Z 01




KZ 30



KZ 93




Z 18



KZ 31



KZ 95



KZ 91H

## Accessories (continued)

Description	For use with		Sold in lots of	Unit reference	Weight kg
Rubber seals for IP 65 degree of protection	Ø 22 mm or 4 hole, front mounting, operating heads with 45 x 45 mm front plate		5	KZ 65	0.003
	Ø 22 mm or 4 hole, front mounting, operating heads with 60 x 60 mm front plate		5	KZ 66	0.004
	Multi-fixing operating heads with 45 x 45 mm front plate		5	KZ 73	0.004
Shaft couplers	⌀ 6 mm shaft	Length = 26 mm	3	KZ 52	0.007
		Length = 60 mm	3	KZ 50	0.013
Terminal covers	Contact blocks	4 contacts	1	KZ 35	0.010
		8 contacts	1	KZ 36	0.020
		12 contacts	1	KZ 37	0.004
		16 contacts	1	KZ 38	0.040
		20 contacts	1	KZ 39	0.050
Nut wrench	M22 fixing nuts		5	Z 01	0.010
Fixing nut, M22	Fixing operating heads on panel or in an enclosure		5	KZ 30	0.007
Mounting adaptor	Converting Ø 30.5 mm fixing hole to Ø 22.5 mm		50	KZ 93	0.003
Keys	8D1 key lock		2	Z 18	0.010
	"Ronis" 8R1 key lock		2	Z 18R1	0.010
	"Ronis" 455 key lock		2	Z 18R	0.010
	"Ronis" 8R15 key lock		2	Z 18R15	0.010
Quick assembly device	Mounting on 35 mm rails to DIN 46277. 2 fixing screws included for rear mounting		5	KZ 31	0.030
Fixing screws 3.5 x 16 mm	4 hole fixing operating heads		100	KZ 95	0.001
Cam switch installation kit Comprising: - mounting plate, - 45 x 45 mm front plate, without legend - black handle, length 35 mm (KZ 27H), - 2 fixing screws	Installation of a cam switch on a distribution panel		1	KZ 91H	0.010

# Cam switches

Complete switches, 12 and 20 A




Operating heads and bodies, front mounting

"Multi-fixing"

By Ø 22 mm hole

With plastic base

With metal base





e: support panel thickness 1 to 6 mm.

Front mounting by 6 screws Ø 5.2 mm and 55 x 100 mm front plate for cam switch with key operated lock

With plastic base and key locking

Panel cut-out




e: support panel thickness 1 to 6 mm.

Type of switch	Operating head + body, front mounting		
	Multi-fixing or by 6 screws Ø 5.2 mm with 55 x 100 mm front plate	By Ø 22 mm hole Plastic base	Metal base
	a	a1	a2
KøA ●●●●, KøB ●●●●	53	70.5	61
KøC ●●●●, KøD ●●●●	63	80.5	71
KøE ●●●●, KøF ●●●●	73	90.5	81
KøG ●●●●, KøH ●●●●	83	100.5	91
KøI ●●●●, KøK ●●●●	93	110.5	101
KøL ●●●●, KøM ●●●●	103	120.5	111
KøN ●●●●, KøO ●●●●	113	130.5	121
KøP ●●●●, KøQ ●●●●	123	140.5	131
KøR ●●●●, KøS ●●●●	133	150.5	141
KøT ●●●●, KøU ●●●●	143	160.5	151


## Bodies

### Front mounting "multi-fixing", 2 or 4 screws




### Front mounting by Ø 22 mm hole

With plastic base




### Front mounting by Ø 22 mm hole

With metal base, secured by needle screws



### Rear mounting




Type of body	Front mounting Multi-fixing		By Ø 22 mm hole		Rear mounting
	a	a1	Plastic base	Metal base	a4
KoA ●●●●, KoB ●●●●	53	77	49	55	42.5
KoC ●●●●, KoD ●●●●	63	87	59	65	52.5
KoE ●●●●, KoF ●●●●	73	97	69	75	62.5
KoG ●●●●, KoH ●●●●	83	107	79	85	72.5
KoI ●●●●, KoK ●●●●	93	117	89	95	82.5
KoL ●●●●, KoM ●●●●	103	127	99	105	92.5
KoN ●●●●, KoO ●●●●	113	137	109	115	102.5
KoP ●●●●, KoQ ●●●●	123	147	119	125	112.5
KoR ●●●●, KoS ●●●●	133	157	129	135	122.5
KoT ●●●●, KoU ●●●●	143	167	139	145	132.5


## Operating heads and legend holders

### For "multi-fixing", front mounting bodies


KoG 3H



KDG 3Y




Panel cut-out (1)




(1) Ø 10 mm central hole for operating shaft access. 2 or 4 holes for cam switch fixings (choice made by installer).

### For Ø 22 mm hole, front mounting bodies - with 45 x 45 mm front plate


KoC 1H, KoC 1H●, KoC 1LH




KCC 1Y




KoC 1S, KoC 1Z



Panel cut-out




KZ 13, KZ 14




## Operating heads and legend holders (continued)

For Ø 22 mm hole, front mounting bodies - with 60 x 60 mm front plate


K●D 1H, KCD 1MH




K●D 1S, K●D 1Z



Panel cut-out




KZ 15, KZ 16




For Ø 22 mm hole, front mounting bodies - with Ø 29 mm metallic finish plastic bezel  
Head + adaptor plate


K●A 1H




K●A 1S, K●A 1Z



Panel cut-out




KZ 01R, KZ 1, KZ 2




For Ø 22 mm hole, front mounting bodies - with Ø 28.5 mm chromium plated metal bezel


KAX Z1M1● + KZ 127




KAX Z1C1● + KZ 127




Panel cut-out



KAX Z1S1● + KZ 127



Panel cut-out



## Operating heads and legend holders (continued)





For 4 hole, rear mounting bodies - with 45 x 45 mm front plate

KOE 1H, KOE 1LH

KCE 1Y

Panel cut-out

KZ 13, KZ 14






For 4 hole, rear mounting bodies - with 60 x 60 mm front plate

KOF 1H, KCF 1MH


Panel cut-out

KZ 15, KZ 16




## Shaft coupler and door interlock

(minimum door opening radius in mm)



## Terminal cover

KZ 3●



## Convention used for switching programme representation



Contact closed



Contact closed in 2 positions and maintained between the 2 positions



Sealed assembly for auto-maintain control




Overlapping contacts



Spring return position: for a switching angle of 90°, spring return is over 30° after the last position (for a maximum of 3 simultaneous contacts).

Example



# Cam switches

Switches mounted in plastic enclosure,  
10 and 16 A

3



KA●●●●●G

## “Emergency stop” switches

- Specifications**
- PVC enclosure.
  - 60 x 60 mm operating head, red handle (without padlocking device) (1) on yellow background. Marking: O I.
  - Legend holder with metallic finish blank legend.

Composition (2)				Thermal current (Ithe) (3)	Reference	Weight
Poles	N	N/O	N/C			
				A		kg
1	-	-	-	10	KA1 A050G	0.365
				16	KA2 A050G	0.365
3	-	-	-	10	KA1 C051G	0.390
				16	KA2 C051G	0.390
3	1	-	-	10	KA1 D052G	0.400
				16	KA2 D052G	0.400
3	-	1	-	10	KA1 D053G	0.400
				16	KA2 D053G	0.400
3	-	1	1	10	KA1 E054G	0.694
				16	KA2 E054G	0.694
3	-	2	2	10	KA1 G055G	0.719
				16	KA2 G055G	0.719
3	1	1	1	10	KA1 F056G	0.704
				16	KA2 F056G	0.704
6	-	-	-	10	KA1 F057G	0.704
				16	KA2 F057G	0.704
6	1	-	-	10	KA1 G058G	0.719
				16	KA2 G058G	0.719
6	-	1	-	10	KA1 G059G	0.719
				16	KA2 G059G	0.719
6	-	1	1	10	KA1 H060G	0.724
				16	KA2 H060G	0.724
9	-	-	-	10	KA1 I061G	0.744
				16	KA2 I061G	0.744
9	1	-	-	10	KA1 K062G	0.749
				16	KA2 K062G	0.719
9	-	1 (4)	-	10	KA1 K063G	0.719
				16	KA2 K063G	0.719

(1) To order a switch with a red padlockable handle (up to 3 padlocks), replace the letter **A** (2<sup>nd</sup> letter) in the references shown above by the letter **C**.  
Example : **KA1 A050G** becomes **KC1 A050G**.

(2) Poles : main contacts  
□ N/O contact : late make (unballasting contact)  
□ N/C contact : signalling contact  
□ Neutral conductor (N) : early make, late break.

(3) Permissible power, AC-23 at 400 V :  
□ K1 switches : 2.2 kW,  
□ K2 switches : 5.5 kW.

(4) Contact not late make.

# Cam switches

Switches mounted in plastic enclosure,  
10 and 16 A



KD●●●●●G

## OFF-ON switches

### Specifications

- PVC enclosure.
- 60 x 60 mm operating head, black handle (without padlocking device) on metallic background. Marking: O I.
- Legend holder with metallic finish blank legend.

Composition (1)				Thermal current (Ithe) (2)	Reference	Weight
Poles	N	N/O	N/C			
				A		kg
1	-	-	-	10	KD1 A050G	0.365
				16	KD2 A050G	0.365
3	-	-	-	10	KD1 C051G	0.390
				16	KD2 C051G	0.390
3	1	-	-	10	KD1 D052G	0.400
				16	KD2 D052G	0.400
3	-	1	-	10	KD1 D053G	0.400
				16	KD2 D053G	0.400
3	-	1	1	10	KD1 E054G	0.694
				16	KD2 E054G	0.694
3	-	2	2	10	KD1 G055G	0.719
				16	KD2 G055G	0.719
3	1	1	1	10	KD1 F056G	0.704
				16	KD2 F056G	0.704
6	-	-	-	10	KD1 F057G	0.704
				16	KD2 F057G	0.704
6	1	-	-	10	KD1 G058G	0.719
				16	KD2 G058G	0.719
6	-	1	-	10	KD1 G059G	0.719
				16	KD2 G059G	0.719
6	-	1	1	10	KD1 H060G	0.724
				16	KD2 H060G	0.724
9	-	-	-	10	KD1 I061G	0.744
				16	KD2 I061G	0.744
9	1	-	-	10	KD1 K062G	0.749
				16	KD2 K062G	0.749
9	-	1 (3)	-	10	KD1 K063G	0.749
				16	KD2 K063G	0.749

(1) Poles : main contacts  
□ N/O contact : late make (unballasting contact)  
□ N/C contact : signalling contact  
□ Neutral conductor (N) : early make, late break.  
(2) Permissible power, AC-23 at 400 V :  
□ K1 switches : 2.2 kW,  
□ K2 switches : 5.5 kW.  
(3) Contact not late make.

Cam switches

Complete switches, 12 A with key operated lock  
Front mounting by 6 screws Ø 5.2 mm  
with 55 x 100 mm front plate

3



K1C 003NZ2

Stepping switches (3 step), without “0” position

Wiring diagram and switching programme	Marking and switch position	Colour of handle	Reference	Weight kg
1-pole				
		Red	K1C 003NZ2	0.170
		Black	K1C 003NZ4	0.170
2-pole				
		Red	K1F 013NZ2	0.170
		Black	K1F 013NZ4	0.170
3-pole				
		Red	K1I 023NZ2	0.170
		Black	K1I 023NZ4	0.170

Cam switches

Complete switches, 12 A with key operated lock  
Front mounting by 6 screws Ø 5.2 mm  
with 55 x 100 mm front plate

Stepping switches (4 step), 4-pole, without “0” position

Wiring diagram and switching programme	Marking and switch position	Colour of handle	Reference	Weight kg
--	-----------------------------	------------------	-----------	-----------

		Red	K1Q 034NZ2	0.170
		Black	K1Q 034NZ4	0.170

4 step with intermediate steps at 30°

		Red	K1Q 8621Z1	0.170

(1) Switching programme identical for 4 step and 4 step with intermediate steps at 30°.










Cam switches

Complete switches, 12 A with key operated lock  
Front mounting by 6 screws Ø 5.2 mm  
with 55 x 100 mm front plate

3



K1D 012QZ2

Stepping switches (2 step), with “0” position				
Wiring diagram and switching programme	Marking and switch position	Colour of handle	Reference	Weight kg
2-pole				
	 	Red          Black	<b>K1D 012QZ2</b>        <b>K1D 012QZ4</b>        	0.170        0.170        
3-pole				
	 	Red          Black	<b>K1F 022QZ2</b>        <b>K1F 022QZ4</b>        	0.170        0.170        
4-pole				
	 	Red          Black	<b>K1H 032QZ2</b>        <b>K1H 032QZ4</b>        	0.170        0.170        



Cam switches

Complete switches, 12 A with key operated lock  
Front mounting by 6 screws Ø 5.2 mm  
with 55 x 100 mm front plate

Stepping switches (3 step), 2-pole, with “0” position

Switching programme	Marking and switch position	Colour of handle	Reference	Weight kg
---------------------	-----------------------------	------------------	-----------	--------------

3 step with intermediate steps at 30°



Red



**K1M 10317Z1** 0.170



Stepping switches (5 step), 2-pole, with “0” position

Wiring diagram and switching programme	Marking and switch position	Colour of handle	Reference	Weight kg
--	-----------------------------	------------------	-----------	--------------

5 step (1)



Red



**K1K 015NZ2** 0.170



Black

**K1K 015NZ4** 0.170

5 step with intermediate steps at 30°



Red

**K1K 1060Z1** 0.170



(1) Switching programme identical for 5 step and 5 step with intermediate steps at 30°.

Cam switches

Complete switches, 12 A with key operated lock  
Front mounting by 6 screws Ø 5.2 mm  
with 55 x 100 mm front plate





K1D 032RZ2

3

Start selector switches (3-position) with “0” position

Switching programme	Marking and switch position	Colour of handle	Reference	Weight kg
---------------------	-----------------------------	------------------	-----------	--------------

1-pole





Red	K1D 032RZ2	0.170



Black	K1D 032RZ4	0.170

2-pole





Red	K1G 043RZ2	0.170



Black	K1G 043RZ4	0.170

2-pole with intermediate positions at 30°



Red	K1I 9289Z1	0.170



## Cam switches

Complete switches, 12 A with key operated lock  
Front mounting by 6 screws Ø 5.2 mm  
with 55 x 100 mm front plate



K1B 001UZ2

### Start selector switches (4-position) with “0” position

Switching programme	Marking and switch position	Colour of handle	Reference	Weight kg
		Red	<b>K1Q 10805Z1</b>	0.170

## Changeover switches with “0” position

[illegible]

## 2-pole

Red

**K1D 002UZ2** 0.170

---



---



---

Black

**K1D 002UZ4** 0.170

---



---



---

### 3-pole

# Cam switches


Complete switches, 32 to 150 A

The range of K30 to K150 cam switches (32 to 150 A ratings) comprises only complete switches.  
These products are more specifically designed for direct control of simple machines.

## Complete switches

- switches
- ON-OFF switches
- changeover switches
- star-delta switches
- pole change switches
- reversing switches

## Front mounting




By 4 holes  
with 64 x 64 mm front plate  
32 to 63 A ratings  
K30, K50 and K63

By 4 holes  
with 88 x 88 mm front plate  
115 to 150 A ratings  
K115 and K150

## "Multi-fixing" mounting

## Rear mounting



By 4 holes on 48 mm centres  
32 to 63 A ratings  
K30, K50 and K63

By 4 holes on 68 mm centres  
115 to 150 A ratings  
K115 and K150

# Cam switches

## Complete switches, 32 to 150 A

Switch type			K30	K50	K63	K115	K150		
Environment characteristics									
Conformity to standards		IEC/EN 60947-3							
Product certifications	cULus	120 V - 1-phase	2 hp	3 hp	3 hp	5 hp	7.5 hp		
		240 V - 1-phase	5 hp	7.5 hp	7.5 hp	10 hp	15 hp		
		240 V - 3-phase	5 hp	7.5 hp	10 hp	20 hp	25 hp		
		480 V - 3-phase	20 hp	25 hp	25 hp	30 hp	40 hp		
Protective treatment		Standard version: "TC"							
Ambient air temperature	For operation	- 25...+ 55 °C							
	For storage	- 40...+ 70 °C							
Electric shock protection		Class II, conforming to IEC 60536 and NF C 20-030							
Degree of protection		IP 40							
Conforming to IEC 529 and NF C 20-010									
Mechanical life		300,000 operating cycles							
Contact block characteristics									
Rated insulation voltage		Ui = 690 V conforming to IEC/EN 60947-1 - Degree of pollution 3							
Conventional thermal current	Screw clamp terminals		In open air	Ith = 32 A	Ith = 50 A	Ith = 63 A	Ith = 115 A	Ith = 150 A	
Rated operational characteristics									
Conforming to IEC/EN 60947-5-1	~ AC-15		220...240 V	14 A	16 A	—	—	—	
			380...440 V	6 A	7 A	—	—	—	
Conforming to IEC/EN 60947-3	~ AC-3	3-phase	220...240 V	5.5 kW	7.5 kW	11 kW	15 kW	22 kW	
			380...440 V	11 kW	15 kW	18.5 kW	30 kW	37 kW	
			660...690 V	11 kW	15 kW	18.5 kW	30 kW	37 kW	
		1-phase	110 V	2.2 kW	2.5 kW	3 kW	3.7 kW	5.5 kW	
			220...240 V	4 kW	5.5 kW	6 kW	7.5 kW	11 kW	
			380...440 V	5.5 kW	7.5 kW	11 kW	13 kW	18.5 kW	
	~ AC-23A	3-phase	220...240 V	7.5 kW	11 kW	15 kW	30 kW	37 kW	
			380...440 V	15 kW	22 kW	30 kW	45 kW	75 kW	
			660...690 V	15 kW	22 kW	55 kW	65 kW	65 kW	
		1-phase	110 V	2.2 kW	2.5 kW	4 kW	5.5 kW	11 kW	
			220...240 V	4 kW	5.5 kW	10 kW	15 kW	22 kW	
			380...440 V	7.5 kW	11 kW	18.5 kW	22 kW	37 kW	
~ AC-21A			32 A	40 A	63 A	100 A	150 A		
Rated conditional short-circuit current		Power: kA	5	5	10	15	25		
Short-circuit protection		Cartridge fuse type gG, A	50	63	80	125	200		
Rated impulse withstand voltage		U imp = 6 kV conforming to IEC/EN 947-1							
Contact operation		Slow break with positive opening operation							
Connection		Captive screw clamp terminals (For 2 x 2.8 x 0.8 mm push-on connectors, please consult your Regional Sales office)							
	Solid cable		2 x 6 mm <sup>2</sup>	2 x 10 mm <sup>2</sup>	2 x 16 mm <sup>2</sup>	1 x 35 mm <sup>2</sup>	1 x 70 mm <sup>2</sup>		
	Flexible cable with or without cable end		2 x 4 mm <sup>2</sup>	2 x 6 mm <sup>2</sup>	2 x 10 mm <sup>2</sup>	1 x 25 mm <sup>2</sup>	1 x 50 mm <sup>2</sup>		
	Tightening torque		1.2 N.m	2 N.m	2.5 N.m	2.5 N.m	2.5 N.m		
Switching capacity ---	Number of contacts in series	1	2	3					
	Resistive load V T ≤ 1 ms	24	48	70	32 A	50 A	63 A	115 A	150 A
		48	95	140	32 A	40 A	63 A	100 A	150 A
		60	120	180	23 A	37 A	30 A	—	—
		110	220	330	6.5 A	—	—	—	—
		220	440	660	1.2 A	—	—	—	—
		440	660	—	0.4 A	—	—	—	—
	Inductive load V T = 50 ms	24	48	70	32 A	40 A	63 A	100 A	150 A
		30	60	90	25 A	30 A	55 A	33 A	50 A
		48	95	140	16 A	20 A	20 A	—	—
		60	120	180	11 A	15 A	—	—	—
		110	220	330	3.2 A	3.5 A	—	—	—

Cam switches

Complete switches, 32 to 150 A  
With 64 x 64 mm front plate (32 to 63 A ratings)  
and 88 x 88 mm front plate (115 and 150 A ratings)

3



K30 C003AP



K50 C003AP

Switches with 45° switching angle					
Front mounting					
Wiring diagram and switching programme	Marking and switch position	Number of poles	Thermal current (Ith) A	Reference	Weight kg
		1	32	K30 A001AP	0.130
			50	K50 A001AP	0.175
		2	32	K30 B002AP	0.170
			50	K50 B002AP	0.215
		3	32	K30 C003AP	0.224
			50	K50 C003AP	0.275
			63	K63 C003AP	0.345
			115	K115 C003AP	0.680
			150	K150 C003AP	0.790
		4	32	K30 D004AP	0.250
			50	K50 D004AP	0.305
			63	K63 D004AP	0.390
			115	K115 D004AP	0.745
			150	K150 D004AP	0.880
		6	32	K30 F006AP	0.425
			50	K50 F006AP	0.530
			63	K63 F006AP	0.590

# Cam switches

Complete switches, 32 to 150 A  
With 64 x 64 mm front plate (32 to 63 A ratings)  
and 88 x 88 mm front plate (115 and 150 A ratings)



K63 C003HP



K150 D004HP

## Switches with 490° switching angle

### Front mounting

Wiring diagram and switching programme	Marking and switch position	Number of poles	Thermal current (Ith) A	Reference	Weight kg
		3	32	K30 C003HP	0.224
			50	K50 C003HP	0.275
			63	K63 C003HP	0.345
			115	K115 C003HP	0.680
			150	K150 C003HP	0.790
		4	32	K30 D004HP	0.250
			50	K50 D004HP	0.305
			63	K63 D004HP	0.390
			115	K115 D004HP	0.745
			150	K150 D004HP	0.880

### Rear mounting

		3	32	K30 C503HP	0.250
			50	K50 C503HP	0.300
			63	K63 C503HP	0.370
			115	K115 C503HP	0.720
			150	K150 C503HP	0.830
		4	32	K30 D504HP	0.280
			50	K50 D504HP	0.350
			63	K63 D504HP	0.440
			115	K115 D504HP	0.790
			150	K150 D504HP	0.930

Cam switches

Complete switches, 32 to 150 A  
With 64 x 64 mm front plate (32 to 63 A ratings)  
and 88 x 88 mm front plate (115 and 150 A ratings)

3



K50 B001UP

Changeover switches with “0” position

Front mounting					
Wiring diagram and switching programme	Marking and switch position	Number of poles	Thermal current (Ith) A	Reference	Weight kg
  1-pole 2-pole 3-pole 4-pole		1	32	K30 B001UP	0.170
			50	K50 B001UP	0.215
			150	K150 B001UP	0.790
		2	32	K30 D002UP	0.250
			50	K50 D002UP	0.305
		3	32	K30 F003UP	0.425
			50	K50 F003UP	0.530
			63	K63 F003UP	0.590
			115	K115 F003UP	0.645
			150	K150 F003UP	0.760
		4	32	K30 H004UP	0.485
			50	K50 H004UP	0.610
			63	K63 H004UP	0.680
			115	K115 H004UP	0.750
			150	K150 H004UP	0.880

Changeover switches without “0” position

Front mounting					
  330 30 1 2 3 4 5 6 7 8 9 10 11 12		3	32	K30 F013UP	0.425
			50	K50 F013UP	0.530
			63	K63 F013UP	0.590
			115	K115 F013UP	0.645
			150	K150 F013UP	0.760
		4	32	K30 H014UP	0.485
			50	K50 H014UP	0.610
			63	K63 H014UP	0.680
			115	K115 H014UP	0.750
			150	K150 H014UP	0.880

Cam switches

Complete switches, 32 to 150 A  
With 64 x 64 mm front plate (32 to 63 A ratings)  
and 88 x 88 mm front plate (115 and 150 A ratings)



K50 H001YP

Star-delta switches					
Front mounting					
Wiring diagram and switching programme	Marking and switch position	Number of poles	Thermal current (Ith) A	Reference	Weight kg
		3	32	K30 H001YP	0.485
			50	K50 H001YP	0.610
			63	K63 H001YP	0.680
			115	K115 H001YP	0.750
			150	K150 H001YP	0.880



K115 K006YP

Reversing star-delta switches					
Front mounting					
Wiring diagram and switching programme	Marking and switch position	Number of poles	Thermal current (Ith) A	Reference	Weight kg
		3	32	K30 K006YP	0.560
			50	K50 K006YP	0.690
			63	K63 K006YP	0.770
			115	K115 K006YP	0.880
			150	K150 K006YP	0.990

Cam switches

Complete switches, 32 to 150 A  
With 64 x 64 mm front plate (32 to 63 A ratings)  
and 88 x 88 mm front plate (115 and 150 A ratings)  
Accessories

3



K63 H004PP



K150 D002WP

Pole change switches for 2-speed motors  
(for motors with tapped “Dahlander” windings)

Front mounting

Wiring diagram and switching programme	Marking and switch position	Number of poles	Thermal current A	Reference	Weight kg
		3	32	K30 H004PP	0.485
			50	K50 H004PP	0.610
			63	K63 H004PP	0.680

Reversing switches with “0” position

Front mounting

		2	32	K30 D002WP	0.250
			50	K50 D002WP	0.305
			63	K63 D002WP	0.390
			115	K115 D002WP	0.745
			150	K150 D002WP	0.880
		3	32	K30 E003WP	0.385
			50	K50 E003WP	0.485
			63	K63 E003WP	0.540
			115	K115 E003WP	0.590
			150	K150 E003WP	0.710

Accessories

Description	For use with	Sold in lots of	Unit reference	Weight kg
Legend holders With blank legend	Square heads 64 x 64 mm	5	KZN 15	0.020
	Square heads 88 x 88 mm	5	KZN 103	0.040
Replacement blank legends for legend holder	KZN 15	5	KZ 77N	0.025
	KZN 103	5	KZ 100N	0.040
Blank legends for metallic finish front plate	64 x 64	5	KZN 21	0.035
	88 x 88	5	KZN 24	0.045


## Cam switches

Complete switches, 32 to 150 A


With 64 x 64 mm front plate (32 to 63 A ratings)  
and 88 x 88 mm front plate (115 and 150 A ratings)

### Cam switches from 32 to 150 A

#### Front mounting




#### Rear mounting



	K30 A K30 B	K30 C K30 D	K30 E K30 F	K30 H	K30 K	K50 A K50 B	K50 C K50 D	K50 E K50 F	K50 H	K50 K	K63 A K63 B	K63 C K63 D	K63 E K63 F	K63 H	K63 K
a	41	53.7	66.4	79.1	104.5	45.8	63.3	80.8	98.3	133.3	49.8	71.3	92.8	114.3	157.3
a1	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6
b	58	58	58	58	58	60	60	60	60	60	66	66	66	66	66
∅	64	64	64	64	64	64	64	64	64	64	64	64	64	64	64
D1	4.1	4.1	4.1	4.1	4.1	4.1	4.1	4.1	4.1	4.1	5.4	5.4	5.4	5.4	5.4
G1	—	48	—	—	—	—	48	—	—	—	—	48	—	—	—
X	—	78 to 97	—	—	—	—	78 to 97	—	—	—	—	78 to 97	—	—	—
	K115 A K115 B	K115 C K115 D	K115 E K115 F	K115 H	K115 K	K150 A K150 B	K150 C K150 D	K150 E K150 F	K150 H	K150 K					
a	61.5	88	114.5	141	194	67.5	100	132.5	165	230					
a1	8.9	8.9	8.9	8.9	8.9	8.9	8.9	8.9	8.9	8.9					
b	84	84	84	84	84	88	88	88	88	88					
∅	88	88	88	88	88	88	88	88	88	88					
D1	5.4	5.4	5.4	5.4	5.4	5.4	5.4	5.4	5.4	5.4					
G1	—	68	—	—	—	—	68	—	—	—					
X	—	120 to 150	—	—	—	—	120 to 150	—	—	—					

e: support panel thickness 0.5 to 5.5 mm.


### Panel cut-out



	K30/K50/K63	K115/K150
D2	4.5	6
D3	10	13
G2	48	68

### Convention used for switching programme representation

Link positions (factory mounted)



Graphic representation of switching positions and spring return to "0" position



Angular position of switch

